



Recommended Driver List

MEGAMAN® RICO Series
Ultra Slim LED Downlight

F27500RC / F27600RC / F28400RC

Wattage: 7W

Input Current: 350mA

Nominal Voltage: DC20V - F27500RC
DC20V - F27600RC
DC18V - F28400RC

Type	Manufacturer	Model No.	Input Voltage (V)	Output Voltage (V)	Output Current (mA)	Lamp Wattage (W)
Non-dimmable	MEGAMAN	LD0208x1d-C350	220-240	DC18-22V	350	7
Triac	MEGAMAN	LD0208x1d-C350	220-240	DC18-22V	350	7
1-10V	Tridonic	LCBI 10W 350mA phase-cut/1-10 V SR	220-240	DC14-28V	350	7
DALI	Meanwell	LCM-25DA	180-277	DC 6-54V	350	7

F29600RC

Wattage: 7W

Input Current: 350mA

Nominal Voltage: DC20V



Type	Manufacturer	Model No.	Input Voltage (V)	Output Voltage (V)	Output Current (mA)	Lamp Wattage (W)
Non-dimmable	MEGAMAN	LD0208x1d-C350	220-240	DC18-22V	350	7
Triac	MEGAMAN	LD0208x1d-C350	220-240	DC18-22V	350	7
1-10V	Tridonic	LCBI 10W 350mA phase-cut/1-10 V SR	220-240	DC14-28V	350	7
DALI	Meanwell	LCM-25DA	180-277	DC 6-54V	350	7

**F29700RC**

Wattage: 12W
Input Current: 350mA
Nominal Voltage: DC36V



Type	Manufacturer	Model No.	Input Voltage (V)	Output Voltage (V)	Output Current (mA)	Lamp Wattage (W)
Non-dimmable	MEGAMAN	LD0212x1-C350	220-240	DC 36V	350	12
Triac	Tridonic	LCBI 20W 350mA phase-cut/1-10 V SR	220-240	DC 27-54V	350	12
1-10V	Tridonic	LCBI 20W 350mA phase-cut/1-10 V SR	220-240	DC 27-54V	350	12
DALI	Meanwell	LCM-25DA	180-277	DC 6-54V	350	12

F29800RC

Wattage: 19W
Input Current: 500mA
Nominal Voltage: DC39V



Type	Manufacturer	Model No.	Input Voltage (V)	Output Voltage (V)	Output Current (mA)	Lamp Wattage (W)
Non-dimmable	MEGAMAN	LD0219x1-C500	220-240	DC 39V	500	19
Triac	Tridonic	LCBI 20W 500mA phase-cut/1-10 V SR	220-240	DC19-38V	500	19
1-10V	MEGAMAN	LD0219x1v-C500	220-240	DC 39V	500	19
DALI	Meanwell	LCM-25DA	180-277	DC 6-50V	500	19

F29900RCv1

Wattage: 25W
Input Current: 700mA
Nominal Voltage: DC36V



Type	Manufacturer	Model No.	Input Voltage (V)	Output Voltage (V)	Output Current (mA)	Lamp Wattage (W)
Non-dimmable	MEGAMAN	LD0425x1-C700	220-240	DC 36V	700	25
Triac	Meanwell	PCD-25-700B	180-295	DC 24-36V	700	25
1-10V	MEGAMAN	LD0425x1v-C700	220-240	DC 36V	700	25
DALI	Meanwell	LCM-25DA	180-277	DC 6-36V	700	25

**F29900RC**

Wattage: 34W

Input Current: 1050mA

Nominal Voltage: DC33V



Type	Manufacturer	Model No.	Input Voltage (V)	Output Voltage (V)	Output Current (mA)	Lamp Wattage (W)
Non-dimmable	MEGAMAN	LD0436x1-C1050	220-240	DC 33V	1050	34
Triac	Meanwell	PCD-40-1050B	180-295	DC 22-38V	1050	34
1-10V	Meanwell	LCM-40	180-295	DC 2-40V	1050	34
DALI	Meanwell	LCM-40DA	180-295	DC 2-40V	1050	34

For the detail specification of the driver, please refer to the manufacturer's specification sheet. The performance depends upon the specification of the driver, which is subject to the status of the manufacturer's technology. Due to possible variations in country driver specifications, please contact your local distributor for a list of suggested drivers before installation.

Copyright © MEGAMAN® 2015. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.