



Dim to **WARM** series

LED AR111

Tested without MEGAMAN® LED Converter



Key

1 to 6	Seamless dimming without flicker point and dimming level to 100% to 5%
1 to 6	Moderate dimming and dimming level to 100% to 20%
	Dimmer not recommended or not tested



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
GP	GP300	250	300	1 to 5	1 to 5
Wonpro	WF Series	250	500	1 to 9	1 to 9
ERA	DG07037	220-240	300	1 to 5	1 to 5
T&J	K211-M2 6L29	230	40-630	1 to 10	1 to 10
Clipsal	3031V500M/K	250	500	1 to 9	1 to 9
Mank	MK/TG100001	250	200	1 to 3	1 to 3
Legrand	YB-CZD	220	40-630	1 to 10	1 to 10
T&J	EC211-1KM2	230	25-1000	1 to 10	1 to 10
Simon	45E101	220	500	1 to 9	1 to 9
Siemens	Vista	220	500	1 to 9	1 to 9
Busch	2210..-510	220-240	60-400	1 to 7	1 to 7
siemens	5UH8722-3NCO3	230	25-400	1 to 7	1 to 7
Clipsal	32E450UDM	220-240	450	1 to 8	1 to 8



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
MK	SX8501	220-240	500	1 to 9	1 to 9
Legrand	281 080	230	500	1 to 9	1 to 9
VS	554591	220-240	5-250	1 to 4	1 to 4
VS	554592	220-240	5-500	1 to 9	1 to 9
Omni	WDM-502	250	500	1 to 9	1 to 9
Clipsal	32E2CFLDM	220-240	5-300	1 to 5	1 to 5
Clipsal	32E450LM	220-240	20-450	1 to 8	1 to 8
Clipsal	32E450TM	220-240	10-450	1 to 8	1 to 8
Clipsal	60TDM	220-240	10-350	1 to 6	1 to 6
Legrand	400T	230-240	10-400	1 to 7	1 to 7
Clipsal	32E450ULM	220-240	450	1 to 8	1 to 8
Vivian	D-21102	220-240	1000	1 to 10	1 to 10
Altenburger	Sim2A	220	60-400	1 to 7	1 to 7
Busch	2210..-510	230	60-400	1 to 7	1 to 7
Merten	5722	230	60-600	1 to 7	1 to 7
Niko	09-013	230	60-300	1 to 5	1 to 5
Niko	310-016	220-240	50-500	1 to 9	1 to 9



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Düwi	8085	230	40-400	1 to 7	1 to 7
PeHa	435 HAN	230	60-600	1 to 10	1 to 10
PeHa	433 HAB	230	20-315	1 to 5	1 to 5
PeHa	434	230	60-400	1 to 7	1 to 7
Düwi	Grundtyp D1	230	60-300	1 to 5	1 to 5
JUNG	1254 UDE	230V	50-420	1 to 7	1 to 7
Düwi	8050	230	40-400	1 to 7	1 to 7
LUMEO	ECO T39.07	230V	7-110	1 to 2	1 to 2
Kopp	80.33	230	40-400	1 to 7	1 to 7
Insta	Berker 2874	230	20-525	1 to 9	1 to 9
Busch	2210-510	220-240	400	1 to 7	1 to 7
Altenburger	EHR600W	220-240	60-600	1 to 10	1 to 10
REV	136231	230V	20-500	1 to 9	1 to 9
REV	136261	230V	20-300	1 to 5	1 to 5
Nisko	DG08050	220-240	1000	1 to 10	1 to 10
Vi-ko	215	220-240	600	1 to 10	1 to 10
Vi-ko	90 30 48	220	600	1 to 10	1 to 10



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Teclastar	45291	220	500	1 to 9	1 to 9
Sica	359901	220	100	1 to 1	1 to 1
Richi	270.15	220	300	1 to 5	1 to 5
Schneider	5510X	220	800	1 to 10	1 to 10
Merlin Gurin	MGU351118	230	400	1 to 7	1 to 7
Dimcontrol	CFL-100	230	1000	1 to 10	1 to 10
Legrand	Neptune 806 15	230	60-500	1 to 9	1 to 9
Legrand	ADW-GL6	230	60-600	1 to 10	1 to 10
Legrand	ADWGL4	220-240	40-400	1 to 7	1 to 7
Everflourish	EFO700DA	220-240	50-300	1 to 5	1 to 5
Busch	2250U	220-240	60-600	1 to 10	1 to 10
Legrand	Mosaic	220-240	60-500	1 to 9	1 to 9
IKEA	E0902-DIM	220-240	25-150	1 to 2	1 to 2
Busch	6513 U102	220-240	420	1 to 7	1 to 7
Busch	2250U	220-240	60-600	1 to 10	1 to 10
Schneider	WDE002747	230	9-100	1 to 1	1 to 1
ABB	6523U	230	2-100(LED)	1 to 9	1 to 9



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Schneider	SBD315RC	230	20-315	1 to 5	1 to 5
Schneider	SBD630RC	230	20-630	1 to 10	1 to 10
Schneider	SBD600RCRL	230	20-600	1 to 10	1 to 10
Schneider	SBD420RCRL	230	20-240	1 to 4	1 to 4
Schneider	SBD200LED	230	4-400	1 to 7	1 to 7
Busch	6591U-101	230	420	1 to 7	1 to 7
Schneider	SBD SPL	230	9-100	1 to 1	1 to 1
Busch	6593U	230	420	1 to 7	1 to 7
ABB	6524U	230	2-100	1 to 1	1 to 1
Schneider	ATTD1000RL	230	60-1000	1 to 10	1 to 10
LUMEO	Domus T39.07	230	7-110	1 to 2	1 to 2
Norvika	200074	250	30-500	1 to 9	1 to 9
Nortronic	ATD500GLE	220-240	50-500	1 to 9	1 to 9
Panasonic	WEJ57515	220	40-500	1 to 9	1 to 9
Elko	400GLI	220-240	40-400	1 to 7	1 to 7
Simon	75313-39	230	40-500	1 to 9	1 to 9
Bticino	CW20 802	250	400	1 to 7	1 to 7



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Simon	Simon..813	220-240	40-500	1 to 9	1 to 9
Gewiss	GW 20 803	230	300	1 to 5	1 to 5
TCL	KGM2	220-240	500	1 to 9	1 to 9
IDV	GKT02	220	500	1 to 9	1 to 9
China IDV	IKT02	220	500	1 to 9	1 to 9
Anam	ASW 3000-1	220-240	60-1000	1 to 10	1 to 10
Stsben	Stsben 86	220	15-200	1 to 3	1 to 3
National	WNG6801	220-240	500	1 to 9	1 to 9
National	WEG57515	220-240	40-500	1 to 9	1 to 9
Garieg	DG04043	220-240	200	1 to 3	1 to 3
ELKO	630GLE	230	40-630	1 to 10	1 to 10
MK	GX8051	220-240	40-500	1 to 9	1 to 9
Soben	DG07079	220-240	630	1 to 10	1 to 10
Clipsal	E3032V500	250	500	1 to 9	1 to 9
LK	SK1	220-240	400	1 to 7	1 to 7
T&J	P2017S	220-240	40-630	1 to 10	1 to 10
Clipsal	32V 500 series	220-240	500	1 to 9	1 to 9



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Keytop	BP1000	220-240	1000	1 to 10	1 to 10
Fungyip	F2771	220-240	500	1 to 9	1 to 9
Clipsal	KB31-RD400	220-240	400	1 to 7	1 to 7
L&K	531556	230V	35-500	1 to 9	1 to 9
BELID	KDT-250E-1	230V	5-250	1 to 4	1 to 4
ELKO	1471444	230V	20-315	1 to 5	1 to 5
KAOYI	KDT-250E	220-240	5-250	1 to 4	1 to 4
Chengli	27V500	250	500	1 to 9	1 to 9
LK	506DA109	230	300	1 to 5	1 to 5
Elako	315GLE	230	40-315	1 to 5	1 to 5
Everflourish	EFO700DB	230	50-300	1 to 5	1 to 5
Elari	ATD300R	230	300	1 to 5	1 to 5
Clipsal	S//E32	250	500	1 to 9	1 to 9
Legrand	BMD 300	100-240	40-300	1 to 5	1 to 5
Legrand	7354 90	230	40-400	1 to 7	1 to 7
Clipsal	F50RD400M	220	400	1 to 7	1 to 7
Schneider	LTD300	230	300	1 to 5	1 to 5



Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Makel	DG07095	230	450	1 to 8	1 to 8
Lightwave	JSJSLW420SS	230	60(LED)	1 to 5	1 to 5
Theben	Dimax 532	230	500	1 to 9	1 to 9
Tridonic	Atco Dali-pcd 300	220-240	30-300	1 to 5	1 to 5
Eltako	EUD12NPN-UC	230	400	1 to 7	1 to 7
Finder	Multifunction dimmer	230	3-500	1 to 9	1 to 9
Eltako	EUD12D-UC	230	400	1 to 7	1 to 7
Leviton	BME04-2L	220	400	1 to 7	1 to 7
Legrand	AR400A3PM	230-240	400	1 to 7	1 to 7
Eltako	EUD61NPN-UC	230	500	1 to 9	1 to 9
EGANT	B327	250V	400	1 to 7	1 to 7
MICRO MATIC	SE45004	230V	5-325	1 to 5	1 to 5
Gira	239000	230	3-100(LED)	1 to 9	1 to 9
Berker	85421200	230	25-400	1 to 7	1 to 7
Eltako	FUD62NPN-230V	230	300	1 to 5	1 to 5
AURORA	AU-DSP400X	240	60-400	1 to 7	1 to 7
MK Black		230	8-48(LED)	1 to 4	1 to 4

Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Varilite	Z0JP250P	230	100(LED)	1 to 9	1 to 9
Zano	ZMC250	230	5-250(LED)	1 to 10	1 to 10
Varilight	JQP401W	230	100(LED)	1 to 1	1 to 1
WILTS	WPDIMWH401	230	7-40(LED)	1 to 3	1 to 3
Schneider	GU6012	200-240	60-400	1 to 7	1 to 7
Denmans	D0017/B	200-240	60-250	1 to 4	1 to 4
Schneider	PDV-TE2100	230-240	5-100	1 to 1	1 to 1
MK	K1523LV/K1524LV	220-240	4-70(LED)	1 to 6	1 to 6
BG	DM400AP	200-250	60-400	1 to 7	1 to 7
Hamilton	H-LEDSTAT	230-240	5-100	1 to 1	1 to 1
DETA		230-240	5-100	1 to 1	1 to 1
Doyle & Tratt		230	100(LED)	1 to 9	1 to 9
Hamilton	LEDITB100	220-240	5-100(LED)	1 to 9	1 to 9
KAOYI	KA-DSP400X	220-240	100(LED)	1 to 9	1 to 9
Busch	2247U	230	500	1 to 9	1 to 9
Jung	225 TDE	230	20-525	1 to 9	1 to 9
Merten	MEG5133-0000	230	40-600	1 to 10	1 to 10

Dim To Warm LED AR111

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR066100/dw/ru-HRv00-NF	LR067100/dw/ru-HRv00-WF
					
Gira	30700	230	20-525	1 to 9	1 to 9
Jung	225 NV DE	230-240	20-500	1 to 9	1 to 9
Merten	MEG5136-0000	230	20-315	1 to 5	1 to 5
Legrand	572213	100-240	40-400	1 to 7	1 to 7
Legrand	281 084	220-240	25-500	1 to 9	1 to 9
LK	506DA124	230	2-180(LED)	1 to 10	1 to 10
LK	506DA218	230	120(LED)	1 to 10	1 to 10
LK	DIMMER 400 UNI IHC/SA	230	40-400	1 to 7	1 to 7
LK	505DA101	230	20-250	1 to 4	1 to 4
SERVODAN	45-001	230	5-100(LED)	1 to 9	1 to 9
LK	Dimmer 1000 LR IHC/SA	230	60-1000	1 to 10	1 to 10
Schneider	CCTDD20016	230	60(LED)	1 to 5	1 to 5
Schneider	CCTDD20017	230	60(LED)	1 to 5	1 to 5
SERVODAN	74-352	230	4-300	1 to 5	1 to 5
Niko	330-00700	230	5-200(LED)	1 to 10	1 to 10
SERVODAN	74-353(MODE 3)	230	4-600	1 to 10	1 to 10
SERVODAN	74-354(MODE 3)	230	4-1000	1 to 10	1 to 10

Remarks

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation.
Copyright © MEGAMAN® 2018. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.