





LED GU9

W Key


1 to 6	Seamless dimming without flicker point and dimming level to 100% to 5%
1 to 6	Moderate dimming and dimming level to 100% to 20%
1 to 6	Dimming with one flicker point
1 to 6	Dimming with one to two flicker points
	Dimmer not recommended or not tested

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
ABB	6523 U	230V	2-100(LED)			1 to 10	1 to 10
BELID	KDT-250E-1	230V	5-250		1 to 10	1 to 10	
Berker	85421200	230	25-400			1 to 10	1 to 10
BG	DM400AP	200-250	60-400				1 to 10
Bticino	M9350S	220-240	500			1 to 10	1 to 10
Busch	6524U	230	2-100	1 to 6			
Busch	6593U	230	420			1 to 10	
China IDV	IKT02	220	500			1 to 10	
Clipsal	3031V500M/K	250	500		1 to 10		1 to 10
Clipsal	32E2CFLDM	220-240	5-300			1 to 10	
Clipsal	32E450TM	220-240	10-450		1 to 10	1 to 10	1 to 10
Clipsal	32E450UDM	220-240	450		1 to 10	1 to 10	

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
Clipsal	32E450ULM	220-240	450		1 to 10		
Clipsal	32V 500 series	250V	500				1 to 10
Clipsal	60TDM	220-240	10-350			1 to 10	1 to 10
Clipsal	E3032V500	250	500		1 to 10	1 to 10	1 to 10
Denmans	D0017/B	200-240	60-250			1 to 10	1 to 10
Dimcontrol	CFL-100	230	1000				1 to 10
Düwi	8085	230	40-400		1 to 10		
EGANT	B327	250V	400			1 to 10	1 to 10
Elako	315GLE	230	40-315		1 to 10		
ELKO	1471444	230V	20-315			1 to 10	
ELKO	630GLE	230	40-630		1 to 10	1 to 10	
Eitako	EUD12D-UC	230	400	1 to 6		1 to 10	1 to 10
Eitako	EUD12NPN-UC	230	400	1 to 6	1 to 10	1 to 10	1 to 10
Eitako	EUD61NPN-UC	230	500	1 to 6		1 to 10	1 to 10
Eitako	FUD62NPN-230V	230	300			1 to 10	1 to 10
ERA	DG07037	220-240	300			1 to 10	1 to 10
Everflourish	EFO700DB	230	50-300			1 to 10	


LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
Finder	Multifunction Dimmer	230	3-500	1 to 6		1 to 10	1 to 10
Fungyip	F2771	220-240	500			1 to 10	
Garieg	DG04043	220-240	200			1 to 10	1 to 8
Gewiss	GW 20 803	230	300			1 to 10	
Gira	30700	230	20-525			1 to 10	
Gira	239000	230	3-100(LED)		1 to 10	1 to 10	1 to 10
GP	GP300	250	300			1 to 10	1 to 10
Hamilton	H-LEDSTAT	230-240	5-100			1 to 5	1 to 4
Hamilton	LEDITB100	220-240	5-100(LED)			1 to 10	1 to 10
IDV	GKT02	220	500			1 to 10	1 to 10
Insta	Berker 2874	230	20-525			1 to 10	
JUNG	1254 UDE	230V	50-420		1 to 10		
Jung	225 NV DE	230-240	20-500		1 to 10		1 to 10
Jung	225 TDE	230	20-525		1 to 10	1 to 10	
KAOYI	KDT-250E	220-240	5-250		1 to 10	1 to 10	
Legrand	572213	100-240	40-400			1 to 10	
Legrand	281 080	230	500		1 to 10		

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
Legrand	400L	230-240	10-400				1 to 10
Legrand	400T	230-240	10-400			1 to 10	
Legrand	6145 25	220-240	25-250			1 to 10	1 to 10
Legrand	AR400A3PM	230-240	400			1 to 10	1 to 10
Legrand	Mosaic	220-240	60-500		1 to 10	1 to 10	1 to 10
Legrand	Neptune 806 15	230	60-500			1 to 10	1 to 10
Legrand	YB-CZD	220	40-630		1 to 10	1 to 10	1 to 10
Leviton	BME04-2L	220	400			1 to 10	1 to 10
Lightwave	JSJSLW420SS	230	60(LED)			1 to 10	
LK	505DA101	230	20-250			1 to 10	
LK	506DA109	230	300			1 to 10	
LK	506DA124	230	2-180(LED)			1 to 10	1 to 10
LK	506DA218	230	120(LED)			1 to 10	
LK	Dimmer 1000 LR IHC/SA	230	60-1000			1 to 10	1 to 10
LK	DIMMER 400 UNI IHC/SA	230	40-400			1 to 10	
LK	SK1	220-240	400		1 to 10	1 to 10	1 to 10
Makel	DG07095	230	450		1 to 10	1 to 10	

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
Mank	MK/TG100001	250	200			1 to 10	1 to 8
Merlin Gurin	MGU351118	230	400			1 to 10	
Merten	MEG5133-0000	230	40-600			1 to 10	1 to 10
Merten	MEG5136-0000	230	20-315			1 to 10	
MICRO MATIC	SE45004	230V	5-325				1 to 10
MK	GX8051	220-240	40-500		1 to 10	1 to 10	
MK	S1535	220-240	1000			1 to 10	
MK	SX8501	220-240	500				1 to 10
National	WEC57515	220	40-500				1 to 10
National	WNG575253	220-240	60-600				1 to 10
National	WNG6801	220-240	500				1 to 10
Niko	310-016	220-240	50-500				1 to 10
Niko	330-00700	230	5-200(LED)			1 to 10	1 to 10
Nisko	DG08050	220-240	1000			1 to 10	1 to 10
Nortronic	ATD500GLE	220-240	50-500		1 to 10	1 to 10	1 to 10
Norvika	200074	250	30-500		1 to 10		1 to 10
Omni	WDM-502	250	500				1 to 10

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
Panasonic	WEJ57515	220	40-500				1 to 10
Peha	433 HAB	230	20-315			1 to 10	
REV	136261	230V	20-300		1 to 10	1 to 10	
Richi	270.15	220	300			1 to 10	1 to 10
Schneider	5510X	220	800			1 to 10	1 to 10
Schneider	C460	220-240	400			1 to 10	1 to 10
Schneider	CCTDD20016	230	60(LED)			1 to 10	1 to 10
Schneider	CCTDD20017	230	60(LED)			1 to 10	1 to 10
Schneider	LTD1000RC	230	1000				1 to 10
Schneider	MEG5170	220-230	10-200		1 to 10		
Schneider	PDV-TE2100	230-240	5-100				1 to 4
Schneider	SBD SPL	230	9-100				1 to 4
Schneider	SBD200LED	230	4-400		1 to 10		1 to 10
Schneider	SBD630RC	230	20-630		1 to 10	1 to 10	
Schneider	WDE002747	230	9-100				1 to 4
SERVODAN	45-001	230	5-100(LED)		1 to 10	1 to 10	
SERVODAN	74-352	230	4-300			1 to 10	1 to 10

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
SERVODAN	74-353(MODE 4)	230	4-600			1 to 10	1 to 10
SERVODAN	74-354(MODE 3)	230	4-1000				1 to 10
SERVODAN	74-354(MODE 4)	230	4-1000			1 to 10	
Sica	359901	220	100		1 to 6	1 to 5	
siemens	5UH8722-3NCO3	230	25-400			1 to 10	
Simen	Simen 55	150-250	40-150			1 to 8	
Simon	45E101	220	500				1 to 10
Simon	Simon..813	220-240	40-500				1 to 10
Soben	DG07079	220-240	630				1 to 10
Stsbén	Stsbén 86	220	15-200		1 to 10	1 to 10	1 to 8
T&J	EC211-1KM2	230	25-1000				1 to 10
T&J	K211-M2 6L29	230	40-630			1 to 10	
T&J	P2017S	220-240	40-630			1 to 10	
TCL	KGM2	220-240	500				1 to 10
TCL	LM2	220	630			1 to 10	1 to 10
Teclastar	45291	220	500			1 to 10	
Theben	Dimax 532	230	500	1 to 6		1 to 10	

LED GU9							
Manufacturer	Model No.	Voltage(V)	Wattage(W)	LU0202d	LU0303d	LU200035/dm-OPv00	LU202045/dm-CSv00
							
Tridonic	Atco Dali-pcd 300	220-240	30-300		1 to 10	1 to 10	1 to 10
Varilight	JQP401W	230	100(LED)				1 to 2
Vi-ko	215	220-240	600			1 to 10	
Vi-ko	90 30 48	220	600			1 to 10	
Vivian	D-21102	220-240	1000			1 to 10	
Wonpro	WF Series	250	500			1 to 10	

Remarks:

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation.
 Copyright © MEGAMAN® 2018. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
 All other trademarks mentioned are the property of their respective owners.