




LED PAR38

Key	
5	maximum number of lamps compatible

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR0920d-25M25D and LR0920d-25M45D
				
Altenburger	EHR600W	220-240	60-600	5
Anam	ASW3000-1	220-240	1000	5
Broco	F25AF	220-240	60-500	5
Busch	2210	220-240	60-400	5
Busch	2210-510	220-240	400	5
Busch	2250U	220-240	60-600	1
Chengli	27V500	250	500	5
Clipsal	32E2CFLDM	220-240	300	5
Clipsal	32V 500 Series	220-240	500	4
Clipsal	S//E32	250	500	5
Crabtree	CRO-1W400	220-240	10-600	5
Dimmalite	EUR400	230	60-400	5
Doyle & Tratt Products	7066	220-240	40-250	5
Doyle & Tratt Products	P400	220-240	60-400	5
Drespa	814	230	60-400	5

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR0920d-25M25D and LR0920d-25M45D
				
Düwi	Grundtyp H1	230	20-500	5
Elko	400GLI	220-240	40-400	5
Eltako	EUD12NPN-UC	230	400	5
Eltako	EUD61NPN-UC	230	500	5
Everfourish	EF0700DA	220-240	50-300	5
Hamilton	L400/2	220-240	400	5
HPM	CAT1000L	220-240	400	5
HPM	CAT400L	220-240	10-400	5
Jung	244EX	220-240	60-400	1
Keytop	BP1000	220-240	1000	5
Legrand	ADWGL4	220-240	40-400	5
Legrand	Haut 100-1000VA	250	100-1000	5
Legrand	Mosaic	220-240	60-500	5
LK	506DA116	230	20-300	3
Merlin Gurin	MGU351118	230	400	5
MK	GX8051	220-240	40-500	5
MK	SX8051	240	40-500	5
National	WEG57515	220-240	40-500	1
National	WNG6801	220-240	500	5
Nibo	09-013	230	60-300	2

Manufacturer	Model No.	Voltage (V)	Wattage (W)	LR0920d-25M25D and LR0920d-25M45D
				
Niko	310-016	220-240	50-500	5
Nortronic	ATD500 GLE	220-240	50-500	5
Omni	WDM-502	250	500	5
Relco	RM0736	220-240	60-500	2
Richmond	GRID400CFL	240	400	5
Richmond	GRID500	240	40-500	5
Richmond	GRID700	240	75-700	5
Schneider	SD300	220-240	300	2
Siemens	Dimmer 15-500W	230	15-500	5
Simon	Simon..813	220-240	40-500	5
Switchlight	SW-316	220-240	500	2
T&J	P2017S	220-240	0-630	1
Theben	Dimax 532	230	500	5
Venus	9720	220	40-900	2
Viko	90 30 48	220	600	5
Vimar	14150	230	100-500	5
Vivian	D-21102	220-240	1000	2

Remarks:

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation.
 Copyright © MEGAMAN® 2016. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
 All other trademarks mentioned are the property of their respective owners.