

LED MR16

Table 1 (page 1-8): 4W to 5W








Table 2 (page 9-15): 6W to 7.5W

Key	
1 to 6	Compatible, with one to six lamps
	The transformer is not tested or not recommended








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Actec	MINI60	230-240	20-60	1 to 2	1 to 3	1 to 2	1 to 1	1 to 1	1 to 1	1 to 2
Actec	VENUS60	230-240	20-60			1 to 2				
Allttx	MT60	230	20-60	1 to 1	1 to 2	1 to 3	1 to 1	1 to 1	1 to 1	
Anchorn	AET-3502R1	220-240	35-150	2 to 6	2 to 6	2 to 6	1 to 4		2 to 6	2 to 3
Andawo	MR-128	220	20-50	1 to 2	1 to 2	1 to 2	1 to 1	1 to 2	1 to 2	
Atom	Tiger	230-240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
Aurora	AU-E60	240	10-60	1 to 3	1 to 3	1 to 3	1 to 1	3 to 3	1 to 3	1 to 3
Barrow	TED20600209-100310	220	20-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
BAW	TREH60C1 6-60w	220	6-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Click	TR060	240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	2 to 2
Collingwood	SKY I 60	240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Crompton	CBC60	240	60			2 to 3				
Dais	DA-J60	240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Dura	DELT12060P	230	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 1








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Dura	DELT12105M	220-240	35-105	2 to 5	2 to 5	2 to 5	1 to 4		2 to 5	2 to 5
Eico	E60W	220-240	10-60	1 to 3			1 to 1		1 to 3	
ELT	TCE 5/23-E	230-240	20-50		1 to 2					1 to 2
ELT	TR 5/23-01-SC	230	50	1 to 2		1 to 2	1 to 1	1 to 2	1 to 2	1 to 2
EMC	ET105	230	35-105	2 to 5	2 to 5	2 to 5	1 to 3	2 to 5	2 to 5	2 to 5
EMC Sp. z o.o	YT70	230	0-70		1 to 3	1 to 3				
Emcolite	EMRED60	240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
Enlite	EN-SC60	240	20-60	1 to 3		1 to 3	1 to 1		2 to 3	1 to 3
ERC	TRAEK02	230	20-60	1 to 3	1 to 3		1 to 1	1 to 3	1 to 3	
Eterna	T60VA	240	20-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Flash Light	HA-105	220-240	35-105	3 to 5	2 to 5	2 to 4	2 to 3		2 to 3	
Flash Light	HA-60	220-240	20-60			1 to 3		2 to 3		2 to 3
FLC	ET60A	230	3-60	1 to 3			1 to 1	1 to 3	1 to 3	
Generic	TE12/70 CODE SB1240-B	220-240	70	1 to 3		1 to 3	1 to 2	1 to 3	1 to 3	
Geni	GT-006	170-240	60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Gentech	Pod E60	220-240	20-60	1 to 3		1 to 3	1 to 1		3 to 3	
Gira	Tronic-Trafo 0366 00	230	20-70	1 to 3	1 to 2	1 to 3	1 to 2	1 to 3	1 to 2	1 to 3
Gira	Tronic-Trafo 0371 00	230-240	20-105		2 to 5		1 to 3		4 to 5	
Gira	Tronic-Trafo 0378 00	230-240	20-105	1 to 5	1 to 5	1 to 5	1 to 3	2 to 5	1 to 5	5 to 5








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Halolite	HA-S105	240	35-105	2 to 5	2 to 5	2 to 5	2 to 3		2 to 2	
Halolite	HA-S60TA	220-240	20-60	1 to 3	1 to 3			2 to 3	1 to 3	1 to 2
Halolite	HA-SE60	240	20-60	2 to 3	1 to 3	1 to 3	1 to 1			
HEP	TB60B 10-60W	230	10-60							1 to 3
HEP Group	TB60I 230 10-60W	230	10-60	1 to 3	1 to 3		1 to 1	1 to 3	1 to 3	1 to 3
HEP Group	TE105S 20-105W	230-240	20-105	1 to 5	1 to 5	1 to 5	1 to 3	1 to 5	1 to 5	1 to 5
HEP Group	TE70S 10-70W	230-240	10-70	1 to 3	1 to 3	1 to 3		1 to 3	1 to 3	1 to 3
HEP Group	TL150S 50-150W	230-240	50-150	3 to 6	3 to 6	3 to 6	1 to 4	3 to 6	3 to 6	3 to 6
HEP Group	TR70 10-70W	230	10-70	1 to 3		1 to 3	1 to 2	1 to 3	1 to 3	
Horoz	HL317	220	105	1 to 5	1 to 5	1 to 5	1 to 4	1 to 5	1 to 5	
JCC	JC4030(10-60AV)	220-240	10-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
Kengo	DET-60S	220-240	10-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Kengo	Ket105	230-240	35-105		2 to 5	2 to 5	1 to 3	2 to 5	2 to 5	
Light Division	ET60A	230	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
Lighttech	LET 105/240	240	35-105	2 to 5		2 to 5	1 to 3		3 to 5	
Lighttech	LET 75/12V	230-240	20-75	1 to 3	1 to 3		1 to 2	3 to 3	3 to 3	
Lightron	ETH-55Eco	240	50	1 to 2	1 to 2	1 to 2	1 to 1	1 to 2	1 to 2	1 to 2
Lite Beetle	LET 105/240LB	240	35-105		2 to 5	2 to 5	1 to 3	2 to 5		
Lite-Tech	SY1507	220-240	20-60							1 to 3








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Lite-Tech	SY1507/W	220-240	20-60	1 to 3	1 to 3	2 to 3	1 to 1		1 to 3	1 to 3
Lival	Pico Wolf 60	220-240	10-60				1 to 1			
Lival	Pico Wolf 70	220-240	20-70	1 to 3	3 to 3	1 to 2	1 to 2	1 to 1	1 to 1	
Loretto	LT60	220-240	20-60	1 to 3		1 to 3	1 to 1	1 to 2	1 to 3	
Lucci	TB60L 240 10-60W	240	10-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Lynx	ET-060-LT-230-RD	230-240	35-60							2 to 3
Massgrove	MT60	240	20-60	1 to 3			1 to 1	3 to 3	1 to 2	
MP Lamp	T60	220-240	10-60	1 to 3		1 to 3		1 to 3	1 to 3	
Nelson	Micro 60	230-240	60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Niko	320-00106	230	20-70	1 to 2	1 to 3	1 to 3	1 to 2	1 to 3	1 to 3	1 to 3
Niko	320-00121	230	20-70	1 to 3	1 to 3	1 to 3	1 to 2	1 to 3	1 to 3	
Nobile	EN-110D2	230	35-110	4 to 5	2 to 5	2 to 5	1 to 3	2 to 5	2 to 5	2 to 5
NVC	AET-60A	220-240	20-60							1 to 3
NVC	ET60DS	220	35-60			2 to 3				
NVC	ET60E	220	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
Online	Pico Wolf 70	230-240	20-70	1 to 2	1 to 2	1 to 2	1 to 2	1 to 1	1 to 1	
Oppl	DB602-220/12	220	20-60	1 to 3		1 to 3	1 to 1		1 to 3	
Orbit Lighting	ET105G(OL105W)	240	35-105	2 to 4			3 to 3		2 to 5	
Orbit Lighting	LET60B	240	10-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Osram	ET-A 60/220-240	220-240	20-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Osram	ET-LED 30/220-240	220-240	2-30	1 to 1				1 to 1	1 to 1	
Osram	ET-P 60/220-240	220-240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Osram	ET-Parrot 105/240 I	240	35-105	2 to 2	2 to 5	2 to 5	1 to 3	2 to 5	2 to 5	2 to 5
Osram	ET-Parrot 70/220-240 I	220-240	20-70				1 to 2		1 to 3	1 to 3
Osram	ET-Redback 60VA/230-240	230-240	20-60			1 to 3	1 to 1	1 to 3	1 to 3	
Osram	ET-Z 60/220-240	220	20-60	1 to 2			1 to 1	1 to 3	1 to 3	
Osram	Halotronic HTM 150/230-240	230-240	50-150	3 to 6		3 to 6	1 to 4	3 to 6	3 to 6	3 to 6
Osram	Halotronic HTM 70/230-240	230-240	20-70	1 to 3	1 to 3	1 to 3	1 to 2		1 to 2	1 to 3
Osram	Halotronic HTN 75/230-240	230-240	20-75							1 to 3
Osram	IZ-A 50/240	240	50	1 to 2			1 to 1	1 to 2	1 to 2	1 to 2
Osram	IZ-Halo 50/220-240	220-240	20-50	1 to 2	1 to 2		1 to 1	1 to 2	1 to 2	1 to 2
Philips	Certaline 60w	230	20-60	1 to 3		1 to 3	1 to 1	1 to 2	1 to 3	
Philips	EHC 075 S	230	20-75		1 to 3			1 to 3		
Philips	EHC250 F	220	35-60	2 to 3		2 to 3	1 to 1	2 to 3	2 to 3	2 to 3
Philips	ET50 220/12V	170-250	40-60	2 to 3			1 to 1	2 to 3	2 to 3	
Philips	ET-E 10	220-240	2-10						1 to 6	
Philips	ET-E 60 220-240	220-240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
Philips	ET-S 105 220-240	220-240	35-105		2 to 5					


LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Philips	ET-S 60 220-240	220-240	20-60	1 to 2		1 to 2	1 to 1		1 to 2	
Philips	Primaline 105 230-240	230-240	35-105	2 to 3	2 to 5	2 to 5	1 to 3		2 to 5	
Philips	Primaline 150 230-240	230-240	50-150	3 to 6	3 to 6	3 to 6	1 to 4		3 to 5	
Philips	Primaline 70 230-240	230-240	20-70	1 to 3		1 to 3	1 to 2	1 to 3	1 to 3	
Puma	ET-075P-230-RD	230-240	35-75	2 to 3		2 to 3	2 to 3	2 to 3	2 to 3	2 to 3
QLT	W60	230	20-60	1 to 3		1 to 3	1 to 1	1 to 3		2 to 3
Radium	ET-Ralopower	230-240	20-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Reico	RN1613	230-240	100-160	5 to 6	1 to 6	1 to 6	1 to 4	5 to 5	5 to 5	5 to 6
Releo	Micro 60 PFS	230-240	10-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	
RIO	RT060CP	220	60	1 to 3				1 to 3	1 to 3	
Robus	LDT150N	230-240	35-150	2 to 3			1 to 4		2 to 6	2 to 5
Robus	LT60d	240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Robus	RM70DN	220-240	20-70	1 to 3		1 to 3	1 to 2	1 to 3	1 to 3	
Sector	ALVT60ED	240	20-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3		
Self	SET105F-2	230	35-105		2 to 5	2 to 3	1 to 3	2 to 1		
Self	SET70F-2	230	20-70	1 to 3	1 to 3		1 to 2	1 to 3	1 to 3	1 to 3
Self	SET70R	220-240	20-70	1 to 3	1 to 3	1 to 3	1 to 2	1 to 3	1 to 3	1 to 3
Skytronic	VWY-006	170-250	20	1 to 1	1 to 1	1 to 6		1 to 1	1 to 1	1 to 1
Sli Sylvania	3006040	240	25-105		2 to 5					2 to 3








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Sylvania	MINI 60	220-240	20-60	1 to 2			1 to 1	1 to 1	1 to 1	
TAO	SET150-2	230	50-150	3 to 6	3 to 6	3 to 6	1 to 4	3 to 6	3 to 6	3 to 6
TAO	SET60LS	220-240	60							1 to 3
TAO	TET-E60I	220	20-60	1 to 3	1 to 3	1 to 3	1 to 1		1 to 3	1 to 3
TCI	MW 70 LED	230-240	1-70	1 to 3	1 to 3	1 to 3	1 to 2	1 to 3	1 to 3	
TCI	Pico Wolf 105	230-240	20-105	1 to 1			1 to 3	1 to 1	1 to 1	1 to 1
TED	WIN-60SLV	220-240	10-60	1 to 3		1 to 3	1 to 1	1 to 3	1 to 3	
Teknolite	Electronic Ballast	230	50							1 to 2
Thorn	ICE742, ECT90-220/12V	220	50							1 to 2
Toroidal Technologies	TRI-50-C	230	50							1 to 1
Tridonic	Atco Possum 60VA 89400035	230-240	60				1 to 1		2 to 3	
Tridonic	Atco Possum 89400085	230-240	60				1 to 1			
Tridonic	Atco Possum TE-0105 C101	230-240	35-105				1 to 3			
Tridonic	Atco Speedy TE-0050 C101	230-240	20-50							2 to 2
Tridonic	Atco Speedy TE-0070 C101	230-240	20-70			1 to 1	1 to 2	2 to 3	2 to 3	
Tridonic	Atco TE-0105 S003	230-240	105	1 to 2	1 to 2	1 to 3	1 to 3			
Tridonic	Atco Viper 60VA 22176070	230-240	60	1 to 3	1 to 3	1 to 3			1 to 3	
Tridonic	Speedy TE-0105 C101	230-240	35-105	2 to 5		2 to 5	1 to 3	2 to 5	2 to 5	
Tridonic	Viper 105 22176074	230-240	105	1 to 5	1 to 5	1 to 5	1 to 3	1 to 5	1 to 5	








LED MR16 4W to 5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER2404DG-WFL ER2404DG-VWFL	ER0604DG-FL	ER2404LN-FL ER2404LN-WFL ER2404LN-VWFL	ER2404.5-35H24D ER2404.5-36H36D	ER3405DG-WFL	ER2405DG-WFL ER2405DG-VWFL	ER2405LN-FL ER2405LN-WFL ER2405LN-VWFL
										
Tridonic	Viper 60 22176072	230-240	60		3 to 3	1 to 2	1 to 1	1 to 3	1 to 3	1 to 1
Tridonic	Viper 60VA 22176110	230	60			1 to 3		1 to 2		
Unotech	UD-105	220-240	35-105		2 to 3	2 to 2				
Unotech	UD-60	220-240	20-60		1 to 3		1 to 1			1 to 3
Ushio Group	456001	230	0-60	1 to 3	1 to 3	1 to 3	1 to 1	1 to 3	1 to 3	1 to 3
Varilight	YT50L	230	0-50			1 to 2				
Voitwell	V3YB-50-B	220	20-50	1 to 2		1 to 2	1 to 1		1 to 2	
Wei Tai	Electronic Transformer	220	60							1 to 2








LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
3E	TFM-60A	220-240	60			1 to 1			1 to 1	
Actec	MINI60	230-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Actec	VENUS60	230-240	20-60			1 to 1			1 to 1	
Allttx	MT60	230	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Anchorn	AET-3502R1	220-240	35-150	1 to 4		1 to 4	2 to 6	1 to 3	1 to 4	1 to 4
Andawo	MR-128	220	20-50	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Atom	Tiger	230-240	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Aurora	AU-E60	240	10-60		1 to 1	1 to 1	1 to 3	1 to 1	1 to 1	1 to 1
Barrow	TED20600209-100310	220	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
BAW	TREH60C1 6-60w	220	6-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Cata Plus	CP-2551	220-240	22-60				2 to 3			
Click	TR060	240	20-60		1 to 1	1 to 1	1 to 3			1 to 1
Collingwood	SKY I 60	240	20-60	1 to 1		1 to 1	1 to 3	1 to 1	1 to 1	1 to 1
Dais	DA-J60	240	20-60	1 to 1		1 to 1	1 to 3	1 to 1	1 to 1	1 to 1
Dura	DELT12060P	230	20-60	1 to 1	1 to 1	1 to 1	1 to 2	1 to 1	1 to 1	1 to 1
Dura	DELT12105M	220-240	35-105	1 to 3		1 to 3	2 to 5	1 to 3	1 to 3	1 to 3
Eico	E60W	220-240	10-60		1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
ELT	TCE 5/23-E	230-240	20-50				1 to 2			
ELT	TR 5/23-01-SC	230	50	1 to 1	1 to 1	1 to 1	1 to 2	1 to 1	1 to 1	1 to 1
EMC	ET105	230	35-105	1 to 3	1 to 3	1 to 3	2 to 5	1 to 2	1 to 3	1 to 3








LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
EMC Sp. z o.o	YT70	230	0-70			1 to 2				
Emcolite	EMRED60	240	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Enlite	EN-SC60	240	20-60		1 to 1	1 to 1	2 to 2	1 to 1		1 to 1
ERC	TRAEK02	230	20-60	1 to 1	1 to 1			1 to 1	1 to 1	1 to 1
Eterna	T60VA	240	20-60	1 to 1		1 to 1		1 to 1	1 to 1	1 to 1
Flash Light	HA-105	220-240	35-105			1 to 3			1 to 1	
Flash Light	HA-60	220-240	20-60		1 to 1	1 to 1	1 to 6			
FLC	ET60A	230	3-60	1 to 1				1 to 1		1 to 1
Generic	TE12/70 CODE SB1240-B	220-240	70	1 to 1	1 to 2	1 to 2		1 to 1	1 to 2	1 to 2
Geni	GT-006	170-240	60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Gentech	Pod E60	220-240	20-60						1 to 1	
Gira	Tronic-Trafo 0366 00	230	20-70	1 to 2	1 to 2	1 to 2	1 to 3	1 to 2	1 to 2	1 to 2
Gira	Tronic-Trafo 0371 00	230-240	20-105		1 to 3	1 to 3	4 to 5	1 to 2	1 to 1	2 to 3
Gira	Tronic-Trafo 0378 00	230-240	20-105		1 to 3	1 to 3	2 to 5	2 to 2	1 to 1	2 to 3
Halolite	HA-S105	240	35-105	1 to 2	3 to 3	1 to 3		2 to 2		3 to 3
Halolite	HA-S60TA	220-240	20-60	1 to 1		1 to 1	1 to 3		1 to 1	
Halolite	HA-SE60	240	20-60		1 to 1	1 to 1		1 to 1	1 to 1	
HEP	TB60B 10-60W	230	10-60				1 to 3			
HEP Group	TB60I 230 10-60W	230	10-60	1 to 1	1 to 1	1 to 1		1 to 1		1 to 1
HEP Group	TE105S 20-105W	230-240	20-105	1 to 3	1 to 3			1 to 2	1 to 3	1 to 3








LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
HEP Group	TE70S 10-70W	230-240	10-70	1 to 2		1 to 2			1 to 2	1 to 2
HEP Group	TL150S 50-150W	230-240	50-150	1 to 4	2 to 4	2 to 4		1 to 3	2 to 4	2 to 4
HEP Group	TR70 10-70W	230	10-70	1 to 2	1 to 2	1 to 2		1 to 1	1 to 2	1 to 2
Horoz	HL317	220	105	1 to 3		1 to 3		1 to 1	1 to 3	1 to 3
JCC	JC4030(10-60AV)	220-240	10-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Kengo	DET-60S	220-240	10-60	1 to 1	1 to 1	1 to 1	1 to 3	1 to 1	1 to 1	1 to 1
Kengo	Ket105	230-240	35-105	1 to 3	1 to 3			1 to 2	1 to 3	
Light Division	ET60A	230	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Lightech	LET 105/240	240	35-105					1 to 2	2 to 3	1 to 3
Lightech	LET 75/12V	230-240	20-75			1 to 6	2 to 3	1 to 1		1 to 2
Lightron	ETH-55Eco	240	50	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Lite Beetle	LET 105/240LB	240	35-105						1 to 3	
Lite-Tech	SY1507	220-240	20-60				1 to 3			
Lite-Tech	SY1507/W	220-240	20-60			1 to 1	1 to 3	1 to 1	1 to 1	1 to 1
Lival	Pico Wolf 60	220-240	10-60		1 to 1			1 to 1	1 to 1	
Lival	Pico Wolf 70	220-240	20-70	1 to 1		1 to 1		1 to 1	1 to 1	1 to 2
Loretto	LT60	220-240	20-60	1 to 1		1 to 1		1 to 1	1 to 1	1 to 1
Lucci	TB60L 240 10-60W	240	10-60	1 to 1	1 to 1	1 to 1	1 to 3	1 to 1	1 to 1	1 to 1
Lynx	ET-060-LT-230-RD	230-240	35-60				2 to 3			
Massgrove	MT60	240	20-60	1 to 1						1 to 1








LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
Meek	ET-60W	230	60	1 to 1	1 to 1					
MP Lamp	T60	220-240	10-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Nelson	Micro 60	230-240	60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Niko	320-00106	230	20-70	2 to 2	1 to 2	1 to 2	1 to 3	1 to 1	1 to 2	1 to 2
Niko	320-00121	230	20-70	1 to 2	1 to 2	1 to 2		1 to 1	1 to 1	1 to 2
Nobile	EN-110D2	230	35-110	1 to 3		1 to 3	2 to 5	1 to 2	1 to 3	1 to 3
NVC	AET-60A	220-240	20-60				1 to 3			
NVC	ET60E	220	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Online	Pico Wolf 60	230-240	10-60				1 to 1		1 to 1	
Online	Pico Wolf 70	230-240	20-70	1 to 1				1 to 1	1 to 1	1 to 1
Oppl	DB602-220/12	220	20-60		1 to 1	1 to 1			1 to 1	1 to 1
Orbit Lighting	ET105G(OL105W)	240	35-105		3 to 3				1 to 1	1 to 3
Orbit Lighting	LET60B	240	10-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Osram	ET-A 60/220-240	220-240	20-60	1 to 1	1 to 1			1 to 1	1 to 1	1 to 1
Osram	ET-LED 30/220-240	220-240	2-30					1 to 1		
Osram	ET-P 60/220-240	220-240	20-60	1 to 1		1 to 1		1 to 1	1 to 1	1 to 1
Osram	ET-Parrot 105/240 I	240	35-105	1 to 2	1 to 3	1 to 3		1 to 2	1 to 3	1 to 3
Osram	ET-Parrot 70/220-240 I	220-240	20-70		1 to 2			1 to 1	1 to 2	1 to 2
Osram	ET-Redback 60VA/230-240	230-240	20-60		1 to 1	1 to 1		1 to 1		1 to 1
Osram	ET-Z 60/220-240	220	20-60	1 to 1	1 to 1			1 to 1	1 to 1	1 to 1




LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
Osram	Halotronic HTM 105/230-240	230-240	35-105			1 to 3				
Osram	Halotronic HTM 150/230-240	230-240	50-150	1 to 4	2 to 3	2 to 4		1 to 3	2 to 4	2 to 4
Osram	Halotronic HTM 70/230-240	230-240	20-70	1 to 2	1 to 2			1 to 1	1 to 2	1 to 2
Osram	IZ-A 50/240	240	50	1 to 1	1 to 1			1 to 1		1 to 1
Osram	IZ-Halo 50/220-240	220-240	20-50	1 to 1	1 to 1			1 to 1	1 to 1	1 to 1
Philips	Certaline 60w	230	20-60		1 to 1			1 to 1	1 to 1	1 to 1
Philips	EHC 075 S	230	20-75	1 to 2						
Philips	EHC250 F	220	35-60	1 to 1	1 to 1	1 to 1	2 to 3	1 to 1	1 to 1	1 to 1
Philips	ET50 220/12V	170-250	40-60	1 to 1					1 to 6	
Philips	ET-E 60 220-240	220-240	20-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Philips	ET-S 105 220-240	220-240	35-105				2 to 5			
Philips	ET-S 60 220-240	220-240	20-60		1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Philips	Primaline 105 230-240	230-240	35-105		1 to 3			1 to 2	1 to 3	1 to 3
Philips	Primaline 150 230-240	230-240	50-150		2 to 4	2 to 4		1 to 3	2 to 4	2 to 4
Philips	Primaline 70 230-240	230-240	20-70	1 to 2	1 to 2			1 to 1	1 to 2	
Puma	ET-075P-230-RD	230-240	35-75	1 to 2	1 to 2	1 to 2	2 to 3	1 to 1	1 to 2	1 to 2
QLT	T105K	230	35-105							2 to 2
QLT	W60	230	20-60		1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Radium	ET-Ralopower	230-240	20-60	1 to 1		1 to 1		1 to 1		1 to 1
Reico	RN1613	230-240	100-160	1 to 3		3 to 4	5 to 6	1 to 3	3 to 4	3 to 4

LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
Releo	Micro 60 PFS	230-240	10-60	1 to 1	1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
RIO	RT060CP	220	60	1 to 1				1 to 1		
Robus	LDT150N	230-240	35-150			1 to 4	2 to 6	1 to 3	1 to 4	1 to 4
Robus	LT60d	240	20-60	1 to 1	1 to 1		1 to 3	1 to 1	1 to 1	1 to 1
Robus	RM70DN	220-240	20-70		1 to 2	1 to 2	1 to 3	1 to 1	1 to 2	1 to 2
Sector	ALVT60ED	240	20-60	1 to 1		1 to 1		1 to 1	1 to 1	1 to 1
Self	SET105F-2	230	35-105	1 to 3		1 to 3		1 to 2	1 to 3	
Self	SET70F-2	230	20-70	1 to 2		1 to 2	1 to 3	1 to 1	1 to 1	1 to 2
Self	SET70R	220-240	20-70	1 to 2	1 to 2	1 to 2	1 to 3	1 to 1	1 to 2	1 to 2
Skytronic	VWY-006	170-250	20				1 to 1			
Sli Sylvania	3006040	240	25-105				3 to 5			
Sylvania	MINI 60	220-240	20-60		1 to 1	1 to 1		1 to 1		1 to 1
TAO	SET150-2	230	50-150		2 to 4	2 to 4	1 to 6	1 to 3	2 to 4	2 to 4
TAO	SET60LS	220-240	60				1 to 3			
TAO	TET-E60I	220	20-60		1 to 1		1 to 3		1 to 1	
TCI	MW 70 LED	230-240	1-70	1 to 2	1 to 2	1 to 2		1 to 1	1 to 2	1 to 2
TCI	Pico Wolf 105	230-240	20-105	1 to 1			1 to 2	1 to 1	1 to 1	1 to 1
TCI	Pico Wolf 60 V.2	230-240	10-60		1 to 1			1 to 1		
TED	WIN-60SLV	220-240	10-60	1 to 1	1 to 1	1 to 1		1 to 1		1 to 1
Thorn	ICE742, ECT90-220/12V	220	50				1 to 2			

LED MR16 6W to 7.5W

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER3406DG-WFL	ER2506DG-WFL	ER2606LN-FL ER2606LN-WFL	ER1006-35H24D ER1006-35H36D	ER3207-50H24D ER3207-50H36D	ER2507.5DG-WFL	ER2607.5LN-FL ER2607.5LN-WFL
										
Toroidal Technologies	TRI-50-C	230	50				1 to 2			
Tridonic	Atco Possum 60VA 89400035	230-240	60		1 to 1	1 to 1		1 to 1	1 to 1	
Tridonic	Atco Possum 89400085	230-240	60		1 to 1	1 to 1	1 to 3		1 to 1	
Tridonic	Atco Possum TE-0105 C101	230-240	35-105		1 to 3	3 to 3	2 to 5			1 to 3
Tridonic	Atco Speedy TE-0050 C101	230-240	20-50				2 to 2			
Tridonic	Atco Speedy TE-0070 C101	230-240	20-70		2 to 2	1 to 2	1 to 3	1 to 1		2 to 2
Tridonic	Atco TE-0105 S003	230-240	105	1 to 1		1 to 1		1 to 1	1 to 1	1 to 1
Tridonic	Atco Viper 60VA 22176070	230-240	60		1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Tridonic	Speedy TE-0105 C101	230-240	35-105		1 to 3			1 to 2	1 to 3	1 to 3
Tridonic	Viper 105 22176074	230-240	105	1 to 3	1 to 3	1 to 3		1 to 2	1 to 3	1 to 3
Tridonic	Viper 60 22176072	230-240	60		1 to 1	1 to 1		1 to 1	1 to 1	1 to 1
Tridonic	Viper 60VA 22176110	230	60	1 to 1	1 to 1	1 to 1		1 to 1		
Unotech	UD-105	220-240	35-105		3 to 3	1 to 1	2 to 3			
Unotech	UD-60	220-240	20-60		1 to 1	1 to 1	1 to 3		1 to 1	
Ushio Group	456001	230	0-60	1 to 1	1 to 1	1 to 1	1 to 3	1 to 1	1 to 1	1 to 2
Voitwell	V3YB-50-B	220	20-50	1 to 1	1 to 1	1 to 1		1 to 1		1 to 1
Wei Tai	Electronic Transformer	220	60				1 to 2			

Remarks:

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the halogen transformer, which is subject to the status of the manufacturer's technology. Due to possible variations in country halogen transformer module specifications, please contact your local distributor for a list of compatible halogen transformers before installation.
Copyright © MEGAMAN® 2016. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.