

LED MR16

Table 1 (page 1-18): Compatible Halogen Transformer List (tested with Dimmers)






Table 2 (page 19-36): Compatible Halogen Transformer List (tested without Dimmer)

Key	
1 to 6	Seamless dimming without flicker point and dimming level to 100% to 5%
1 to 6	Moderate dimming and dimming level to 100% to 20%
1 to 6	Dimming with one flicker point
1 to 6	Dimming with one to two flicker points
	Dimmer not recommended or not tested






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
ELT	TCE 523 E	Simon	75305-69	230	40-500	1 to 1	1 to 1	1 to 1		
ELT	TCE 523 E	Simon	Simon 32813-35	220-240	40-500	1 to 1	1 to 1	1 to 1		
Online	Pioc Wolf 60	ABB	6523U	230	2-100	1 to 1	1 to 1	1 to 1		
Online	Pioc Wolf 60	Busch	2210...-510	230	60-400	1 to 1	1 to 1	1 to 1		
Online	Pioc Wolf 60	Schneider	WDE002747	230	9-100	1 to 1	1 to 1	1 to 1		
Online	Pioc Wolf 70	ABB	6523U	230	2-100	1 to 2	1 to 2	1 to 2		
Online	Pioc Wolf 70	Schneider	WDE002747	230	9-100	1 to 2	1 to 2	1 to 2		
Osram	ET-PARROT 70	Altenburger	Sim2A	220	60-400				1 to 2	1 to 2
Osram	ET-PARROT 70	Altenburger Electronic	EHR600W	220-240	60-600				1 to 1	1 to 1
Osram	ET-PARROT 70	Anam	ASW3000-1	220-240	1000				1 to 1	1 to 1
Osram	ET-PARROT 70	Broco	F25AF	220-240	60-500				1 to 1	1 to 1
Osram	ET-PARROT 70	Busch	2210...-510	230	60-400	1 to 2	1 to 2	1 to 2	1 to 2	1 to 2






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	ET-PARROT 70	Busch	2210-510	220-240	400				1 to 2	1 to 2
Osram	ET-PARROT 70	Busch	2250U	220-240	60-600				1 to 2	1 to 2
Osram	ET-PARROT 70	Busch	6513 U102	220-240	420				1 to 2	1 to 2
Osram	ET-PARROT 70	Chengli	27V500	250	500				2 to 2	2 to 2
Osram	ET-PARROT 70	China IDV	IKTO2	220	500	1 to 2	1 to 2	1 to 2		
Osram	ET-PARROT 70	Clipsal	32E2CFLDM	220-240	300				1 to 2	1 to 2
Osram	ET-PARROT 70	Clipsal	32V 500 Series	220-240	500				1 to 2	1 to 2
Osram	ET-PARROT 70	Contactum	P400	216-253	60-400				1 to 2	1 to 2
Osram	ET-PARROT 70	Crabtree	CRO-1W400	220-240	10-600				1 to 2	1 to 2
Osram	ET-PARROT 70	Dimmalite	EUR400	230	60-400				1 to 2	1 to 2
Osram	ET-PARROT 70	Doyle & Tratt Products	7066	220-240	40-250				1 to 2	1 to 2
Osram	ET-PARROT 70	Doyle & Tratt Products	P400	220-240	60-400				1 to 1	1 to 1
Osram	ET-PARROT 70	Düwi	Grundtyp H1	230	20-500				1 to 2	1 to 2
Osram	ET-PARROT 70	Elako	315GLE	230	40-315				1 to 2	1 to 2
Osram	ET-PARROT 70	Elko	400GLI	220-240	40-400				2 to 2	2 to 2
Osram	ET-PARROT 70	Fungyip	F2771	220-240	500				1 to 1	1 to 1






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	ET-PARROT 70	GE	37/56	230	40-500				1 to 2	1 to 2
Osram	ET-PARROT 70	GET	GET 60-400W	220-240	60-400				1 to 1	1 to 1
Osram	ET-PARROT 70	GET	R25E	200-250	60-250				1 to 2	1 to 2
Osram	ET-PARROT 70	Keytop	BP1000	220-240	1000				1 to 2	1 to 2
Osram	ET-PARROT 70	Legrand	ADWGL4	220-240	40-400				1 to 2	1 to 2
Osram	ET-PARROT 70	LK	506DA116	230	20-300				1 to 2	1 to 2
Osram	ET-PARROT 70	Mank	MK/TG100001	250	200	1 to 2	1 to 2	1 to 2		
Osram	ET-PARROT 70	Merlin Gurin	MGU351118	230	400				1 to 2	1 to 2
Osram	ET-PARROT 70	MK	42804PL	230	40-250				1 to 2	1 to 2
Osram	ET-PARROT 70	MK	GX8051	220-240	40-500				1 to 2	1 to 2
Osram	ET-PARROT 70	MK	SX8051	240	40-500				1 to 2	1 to 2
Osram	ET-PARROT 70	National	WNG6801	220-240	500				1 to 2	1 to 2
Osram	ET-PARROT 70	Niko	310-016	220-240	50-500				2 to 2	2 to 2
Osram	ET-PARROT 70	Nortronic	ATD500 GLE	220-240	50-500				1 to 2	1 to 2
Osram	ET-PARROT 70	Omni	WDM-502	250	500				1 to 1	1 to 1
Osram	ET-PARROT 70	POL	CAT 1593M	220-240	500	1 to 2	1 to 2	1 to 2	1 to 1	1 to 1

Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	ET-PARROT 70	Relco Relco	RM0736	220-240	60-500				1 to 2	1 to 2
Osram	ET-PARROT 70	Richmond	GRID400CFL	240	400				1 to 2	1 to 2
Osram	ET-PARROT 70	Richmond	GRID500	240	40-500				1 to 2	1 to 2
Osram	ET-PARROT 70	Schneider	ATD315	220-240					1 to 2	1 to 2
Osram	ET-PARROT 70	Schneider	C460	220	400	2 to 2	2 to 2	2 to 2		
Osram	ET-PARROT 70	Schneider	SD300	220-240	300				1 to 2	1 to 2
Osram	ET-PARROT 70	Simen	Simen 55	150-250	40-150	1 to 2	1 to 2	1 to 2		
Osram	ET-PARROT 70	Simon	Simon 32813-35	220-240	40-500				1 to 2	1 to 2
Osram	ET-PARROT 70	Soben	C8M2	200-250	630	1 to 2	1 to 2	1 to 2		
Osram	ET-PARROT 70	Stsben	Stsben 86	220	15-200	1 to 2	1 to 2	1 to 2		
Osram	ET-PARROT 70	Switchlight	SW-316	220-240	500				1 to 2	1 to 2
Osram	ET-PARROT 70	T&J	K211-M2 6L29	230	40-630	1 to 2	1 to 2	1 to 2	1 to 2	1 to 2
Osram	ET-PARROT 70	T&J	P2017S	220-240	0-630				1 to 2	1 to 2
Osram	ET-PARROT 70	Venus	ART:9720	220	40-900				1 to 2	1 to 2
Osram	ET-PARROT 70	Viko	90 30 48	220	600				1 to 2	1 to 2
Osram	ET-PARROT 70	Vimar	14150	230	100-500				1 to 2	1 to 2






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	ET-PARROT 70	Vivian	D-21102	220-240	1000				1 to 2	1 to 2
Osram	ET-PARROT 70	Wonpro	WF Series	250	500	1 to 2	1 to 2	1 to 2	1 to 2	1 to 2
Osram	Halotronic HTM 150	Altenburger	EHR600W	220-240	60-600	2 to 4	2 to 4	2 to 4		
Osram	Halotronic HTM 150	Altenburger	Sim2A	220	60-400	1 to 3	1 to 3	1 to 3		
Osram	Halotronic HTM 150	Busch	2210-510	220-240	400	2 to 4	2 to 4	2 to 4		
Osram	Halotronic HTM 150	Busch	2250U	220-240	60-600	2 to 4	2 to 4	2 to 4		
Osram	Halotronic HTM 150	Busch	6524U	230	2-100	1 to 2	1 to 2	1 to 2		
Osram	Halotronic HTM 150	Düwi	Grundtyp H1	230	20-500	2 to 4	2 to 4	2 to 4		
Osram	Halotronic HTM 150	Insta	Berker 2874	230	20-525	1 to 4	1 to 4	1 to 4		
Osram	Halotronic HTM 150	Jung	244EX	220-240	60-400	2 to 4	2 to 4	2 to 4		
Osram	Halotronic HTM 150	Merten	5778	220-230	20-315	1 to 3	1 to 3	1 to 3		
Osram	Halotronic HTM 150	Niko	310-016	220-240	50-500	2 to 4	2 to 4	2 to 4		
Osram	Halotronic HTM 70	Elko	400GLI	220-240	40-400	1 to 2	1 to 2	1 to 2		
Osram	Halotronic HTM 70	Gira	3000	230	20-500	1 to 2	1 to 2	1 to 2		
Osram	Halotronic HTM 70	Insta	Gira 1176 00/ I00	230	50-420	1 to 2	1 to 2	1 to 2		
Osram	Halotronic HTM 70	Nortronic	ATD500 GLE	220-240	50-500	2 to 2	2 to 2	2 to 2		






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	Halotronic HTM 70	Panasonic	WEJ57515	220	40-500	1 to 2	1 to 2	1 to 2		
Osram	Halotronic HTM 70	Schneider	SD300	220-240	300	1 to 2	1 to 2	1 to 2		
Osram	HTM105	Altenburger	EHR600W	220-240	60-600				1 to 3	1 to 3
Osram	HTM105	Altenburger	Sim2A	220	60-400				1 to 3	1 to 3
Osram	HTM105	Anam	ASW3000-1	220-240	1000				1 to 1	1 to 1
Osram	HTM105	Broco	F25AF	220-240	60-500				1 to 2	1 to 2
Osram	HTM105	Busch	2210...-510	230	60-400				1 to 3	1 to 3
Osram	HTM105	Busch	2210-510	220-240	400				1 to 3	1 to 3
Osram	HTM105	Busch	2250U	220-240	60-600				1 to 3	1 to 3
Osram	HTM105	Busch	6513 U102	220-240	420				1 to 3	1 to 3
Osram	HTM105	Chengli	27V500	250	500				2 to 3	2 to 3
Osram	HTM105	Clipsal	32E2CFLDM	220-240	300				1 to 3	1 to 3
Osram	HTM105	Clipsal	32V 500 Series	220-240	500				1 to 3	1 to 3
Osram	HTM105	Contactum	P400	216-253	60-400				1 to 3	1 to 3
Osram	HTM105	Crabtree	CRO-1W400	220-240	10-600				2 to 3	2 to 3
Osram	HTM105	Dimmalite	EUR400	230	60-400				2 to 3	2 to 3






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	HTM105	Doyle & Tratt Products	7066	220-240	40-250				1 to 3	1 to 3
Osram	HTM105	Doyle & Tratt Products	P400	220-240	60-400				1 to 3	1 to 3
Osram	HTM105	Düwi	Grundtyp H1	230	20-500				1 to 3	1 to 3
Osram	HTM105	Elako	315GLE	230	40-315				1 to 3	1 to 3
Osram	HTM105	Elko	400GLI	220-240	40-400				2 to 3	2 to 3
Osram	HTM105	Everfourish	EF0700DA	220-240	50-300				1 to 1	1 to 1
Osram	HTM105	Fungyip	F2771	220-240	500				2 to 2	2 to 2
Osram	HTM105	GE	37/56	230	40-500				1 to 3	1 to 3
Osram	HTM105	GET	GET 60-400W	220-240	60-400				1 to 3	1 to 3
Osram	HTM105	GET	R25E	200-250	60-250				1 to 3	1 to 3
Osram	HTM105	Keytop	BP1000	220-240	1000				1 to 3	1 to 3
Osram	HTM105	Legrand	ADWGL4	220-240	40-400				1 to 3	1 to 3
Osram	HTM105	Legrand	Mosaic	220-240	60-500				1 to 3	1 to 3
Osram	HTM105	LK	506DA116	230	20-300				1 to 3	1 to 3
Osram	HTM105	Merlin Gurin	MGU351118	230	400				2 to 3	2 to 3
Osram	HTM105	MK	42804PL	230	40-250				1 to 3	1 to 3


Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	HTM105	MK	GX8051	220-240	40-500				1 to 3	1 to 3
Osram	HTM105	MK	SX8051	240	40-500				1 to 3	1 to 3
Osram	HTM105	National	WEG57515	220-240	40-500				1 to 2	1 to 2
Osram	HTM105	National	WNG6801	220-240	500				2 to 3	2 to 3
Osram	HTM105	Niko	310-016	220-240	50-500				2 to 2	2 to 2
Osram	HTM105	Nortronic	ATD500 GLE	220-240	50-500				1 to 3	1 to 3
Osram	HTM105	Omni	WDM-502	250	500				1 to 3	1 to 3
Osram	HTM105	Relco Relco	RM0736	220-240	60-500				2 to 3	2 to 3
Osram	HTM105	Richmond	GRID400CFL	240	400				1 to 3	1 to 3
Osram	HTM105	Richmond	GRID500	240	40-500				1 to 3	1 to 3
Osram	HTM105	Richmond	GRID700	240	75-700				2 to 3	2 to 3
Osram	HTM105	Schneider	ATD315	220-240					1 to 3	1 to 3
Osram	HTM105	Simon	Simon 32813-35	220-240	40-500				1 to 3	1 to 3
Osram	HTM105	Switchlight	SW-316	220-240	500				2 to 2	2 to 2
Osram	HTM105	T&J	K211-M2 6L29	230	40-630				1 to 3	1 to 3
Osram	HTM105	Venus	ART:9720	220	40-900				1 to 2	1 to 2






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	HTM105	Viko	90 30 48	220	600				1 to 3	1 to 3
Osram	HTM105	Vimar	14150	230	100-500				1 to 3	1 to 3
Osram	HTM105	Vivian	D-21102	220-240	1000				1 to 3	1 to 3
Osram	HTM105	Wonpro	WF Series	250	500				1 to 3	1 to 3
Philips	EHC 075 s	Clipsal	32V 500 series	220-240	500	1 to 2	1 to 2	1 to 2		
Philips	EHC 075 s	Fungyip	F2771	220-240	500	1 to 2	1 to 2	1 to 2		
Philips	EHC 075 s	Keytop	BP1000	220-240	1000	1 to 2	1 to 2	1 to 2		
Philips	EHC 075 s	Leviton	BME04-2L	220	400	1 to 2	1 to 2	1 to 2		
Philips	EHC 075 s	MK	GX8051	220-240	40-500	1 to 2	1 to 2	1 to 2		
Philips	EHC 075 s	T&J	P2017S	220-240	0-630	1 to 2	1 to 2	1 to 2		
Philips	ET-E60	Mank	MK/TG100001	250	200	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	Schneider	C460	220	400	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	Stsben	Stsben 86	220	15-200	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	TCL	KGM2	220-240	500	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	TCL	LM2	220	630	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	Wonpro	WF Series	250	500	1 to 1	1 to 1	1 to 1		






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Philips	ET-S 60 220-240	Clipsal	32V 500 Series	220-240	500	1 to 1	1 to 1	1 to 1		
Philips	ET-S 60 220-240	Fungyip	F2771	220-240	500	1 to 1	1 to 1	1 to 1		
Philips	ET-S 60 220-240	Keytop	BP1000	220-240	1000	1 to 1	1 to 1	1 to 1		
Philips	ET-S 60 220-240	Leviton	BME04-2L	220	400	1 to 1	1 to 1	1 to 1		
Philips	ET-S 60 220-240	MK	GX8051	220-240	40-500	1 to 1	1 to 1	1 to 1		
Philips	ET-S 60 220-240	T&J	P2017S	220-240	0-630	1 to 1	1 to 1	1 to 1		
Philips	Primaline 70	Altenburger	EHR600W	220-240	60-600	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Altenburger	Sim2A	220	60-400	2 to 2	2 to 2	2 to 2		
Philips	Primaline 70	Busch	2210-510	220-240	400	2 to 2	2 to 2	2 to 2		
Philips	Primaline 70	Busch	2250U	220-240	60-600	2 to 2	2 to 2	2 to 2		
Philips	Primaline 70	Busch	6524U	230	2-100	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Düwi	Grundtyp H1	230	20-500	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Elko	400GLI	220-240	40-400	2 to 2	2 to 2	2 to 2		
Philips	Primaline 70	Gira	3000	230	20-500	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Insta	Berker 2874	230	20-525	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Insta	Gira 1176 00/ I00	230	50-420	1 to 2	1 to 2	1 to 2		






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Philips	Primaline 70	Jung	244EX	220-240	60-400	2 to 2	2 to 2	2 to 2		
Philips	Primaline 70	Merten	5770	220-230	20-315	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Merten	5778	220-230	20-315	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Niko	09-013	230	60-300	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Niko	310-016	220-240	50-500	2 to 2	2 to 2	2 to 2		
Philips	Primaline 70	Nortronic	ATD500 GLE	220-240	50-500	1 to 2	1 to 2	1 to 2		
Philips	Primaline 70	Schneider	SD300	220-240	300	2 to 2	2 to 2	2 to 2		
TCI	MW 70 LED	Busch	2250U	220-240	60-600				1 to 1	1 to 1
TCI	MW 70 LED	Busch	6513 U102	220-240	420				2 to 2	2 to 2
TCI	MW 70 LED	Clipsal	32E2CFLDM	220-240	300				1 to 2	1 to 2
TCI	MW 70 LED	Düwi	Grundtyp H1	230	20-500				1 to 2	1 to 2
TCI	MW 70 LED	Elako	315GLE	230	40-315				1 to 2	1 to 2
TCI	MW 70 LED	HPM	CAT1000L	220-240	400				1 to 1	1 to 1
TCI	MW 70 LED	Legrand	Mosaic	220-240	60-500				2 to 2	2 to 2
TCI	MW 70 LED	LK	506DA116	230	20-300				1 to 2	1 to 2
TCI	MW 70 LED	MK	SX8051	240	40-500				1 to 1	1 to 1






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
TCI	MW 70 LED	Nortronic	ATD500 GLE	220-240	50-500				1 to 2	1 to 2
TCI	MW 70 LED	Relco Relco	RM0736	220-240	60-500				1 to 1	1 to 1
TCI	MW 70 LED	Richmond	GRID700	240	75-700				2 to 2	2 to 2
TCI	MW 70 LED	Schneider	ATD315	220-240	-				1 to 2	1 to 2
TCI	MW 70 LED	Simon	Simon 32813-35	220-240	40-500				1 to 1	1 to 1
TCI	MW 70 LED	T&J	K211-M2 6L29	230	40-630				1 to 2	1 to 2
Tridonic	Atco 22176070	Aurora	AU-DSP400	240	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Aurora	AU-DSP400X	240	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	British General	AT091-BG	200-250	60-500	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Crabtree	CPU-2W400	200-240	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Danlers	DR1D400w	230	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Denmans	HDP-400	200-240	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Deta	DEP-250DT	200-240	35-250	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Deta	DEP-400DT	200-240	35-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Doyle & Tratt Products	7066	220-240	40-250	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Doyle & Tratt Products	P400	220-240	60-400	1 to 1	1 to 1	1 to 1		






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Tridonic	Atco 22176070	GET	EN60669	220-240	250	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	GET	R25E	200-250	60-250	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Home Automation	VID dimr100e	200-250	50-500	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	MK	42804PL	230	40-250	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	MK	L/N1511	230	60-450	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Richmond	MP500	230	40-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Richmond	GRID500	240	40-500	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Schneider	GU6012	220-240	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Varilight	TQP501W	216-253	60-500	1 to 1	1 to 1	1 to 1		




Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	ET-A 60	GP	GP300	250	300	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Wonpro	WF Series	250	500	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	ERA	DG07037	220-240	300	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	T&J	K211-M2 6L29	230	40-630	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Clipsal	3031V500M/K	250	500	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Mank	MK/TG100001	250	200	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Schneider	C460	220-240	400	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Legrand	YB-CZD	220	40-630	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	T&J	EC211-1KM2	230	25-1000	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Simon	45E101	220	500	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Siemens	Vista	220	500	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	siemens	5UH8722-3NCO3	230	25-400	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Soben	C8M2	200-250	630	1to1	1to1	1to1	1 to 1	1 to 1
Osram	ET-A 60	China IDV	IKT02	220	500				1 to 1	1 to 1
Osram	ET-A 60	Clipsal	EV51RD400	220	400	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Stsben	Stsben 86	220	15-200	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	ET-A 60	ABB		250	600	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Simen	Simen 55	150-250	40-150	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Garieg	DG04043	220-240	200	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	POL	CAT 1593M	220-240	500	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-A 60	Igoto	DG04041	220-240	200	1 to 1	1 to 1	1 to 1		
Osram	ET-A 60	TCL	KGM2	220-240	500	1 to 1	1 to 1	1 to 1		
Osram	ET-A 60	TCL	LM2	220	630	1 to 1	1 to 1	1 to 1		
Osram	ET-A 60	National	WEC57515	220	40-500	1 to 1	1 to 1	1 to 1		
Osram	ET-A 60	BOLATU		220	400W	1 to 1	1 to 1	1 to 1		
Osram	Halotronic HTM 150	PeHa	435 HAN	230	60-600				1 to 1	1 to 1
Osram	Halotronic HTM 150	PeHa	433 HAB	230	20-315				1 to 1	1 to 1
Osram	Halotronic HTM 150	Düwi	Grundtyp D1	230	60-300	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	Halotronic HTM 150	JUNG	1254 UDE	230V	50-420				1 to 1	1 to 1
Osram	Halotronic HTM 150	Düwi	8050	230	40-400				1 to 1	1 to 1
Osram	Halotronic HTM 150	LUMEO	ECO T39.07	230V	7-110				1 to 1	1 to 1
Osram	Halotronic HTM 150	Kopp	80.33	230	40-400				1 to 1	1 to 1






Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	Halotronic HTM 150	REV	136261	230V	20-300				1 to 1	1 to 1
Osram	Halotronic HTM 150	Theben	Dimax 532	230	500				1 to 1	1 to 1
Osram	Halotronic HTM 150	Eltako	EUD12NPN-UC	230	400				1 to 1	1 to 1
Osram	Halotronic HTM 150	Eltako	EUD12D-UC	230	400				1 to 1	1 to 1
Osram	Halotronic HTM 150	Leviton	BME04-2L	220	400				1 to 1	1 to 1
Osram	Halotronic HTM 150	Eltako	EUD61NPN-UC	230	500				1 to 1	1 to 1
Osram	Halotronic HTM 150	Gira	239000	230	3-100(LED)				1 to 1	1 to 1
Osram	Halotronic HTM 150	Berker	85421200	230	25-400				1 to 1	1 to 1
Osram	Halotronic HTM 150	Eltako	FUD62NPN-230V	230	300				1 to 1	1 to 1
Osram	Halotronic HTM 150	Jung	225 TDE	230	20-525				1 to 1	1 to 1
Osram	Halotronic HTM 150	Merten	MEG5133-0000	230	40-600				1 to 1	1 to 1
Osram	Halotronic HTM 150	Gira	30700	230	20-525				1 to 1	1 to 1
Osram	Halotronic HTM 150	Jung	225 NV DE	230-240	20-500				1 to 1	1 to 1
Osram	Halotronic HTM 150	Merten	MEG5136-0000	230	20-315				1 to 1	1 to 1
Osram	Halotronic HTM 150	Altenburger	EHR600W	220-240	60-600				1 to 1	1 to 1
Osram	Halotronic HTM 150	Busch	6524U	230	2-100				1 to 1	1 to 1

Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Osram	Halotronic HTM 150	Düwi	Grundtyp H1	230	20-500				1 to 1	1 to 1
Osram	Halotronic HTM 150	Jung	244EX	220-240	60-400				1 to 1	1 to 1
Osram	Halotronic HTM 70	Elko	400GLI	220-240	40-400				1 to 1	1 to 1
Philips	ET-E60	ERA	DG07037	220-240	300	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Philips	ET-E60	Simon	45E101	220	500	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Philips	ET-E60	Siemens	Vista	220	500				1 to 1	1 to 1
Philips	ET-E60	Stsben	Stsben 86	220	15-200	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	TCL	KGM2	220-240	500	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	Wonpro	WF Series	250	500	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	GP	GP300	250	300	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	National	WEC57515	220	40-500	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	Simen	Simen 55	150-250	40-150	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	Garieg	DG04043	220-240	200	1 to 1	1 to 1	1 to 1		
Philips	ET-E60	BOLATU		220	400W	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	Aurora	AU-DSP400X	240	60-400	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	JSJS Designs	JSJSLW420	220-240	20-250	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1

Compatible Halogen Transformer List (tested with Dimmers)

Halogen Transformer		Dimmer				ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF
Manufacturer	Model No.	Manufacturer	Model No.	Voltage (V)	Wattage (W)					
Tridonic	Atco 22176070	MK Black		230	8-48(LED)				1 to 1	1 to 1
Tridonic	Atco 22176070	Varilite	Z0JP250P	230	100(LED)	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Tridonic	Atco 22176070	Varilight	JQP401W	230	100(LED)				1 to 1	1 to 1
Tridonic	Atco 22176070	Schneider	GU6012	200-240	60-400				1 to 1	1 to 1
Tridonic	Atco 22176070	Schneider	PDV-TE2100	230-240	5-100				1 to 1	1 to 1
Tridonic	Atco 22176070	Doyle & Tratt		230	100(LED)				1 to 1	1 to 1
Tridonic	Atco 22176070	Denmans	D0017/B	200-240	60-250	1 to 1	1 to 1	1 to 1		
Tridonic	Atco 22176070	BG	DM400AP	200-250	60-400	1 to 1	1 to 1	1 to 1		

Key	
1 to 2	Compatible, with one to two lamps
	The transformer are not tested or not recommended

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
Ushio Group	456001	230	0-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Unotech	UD-105	220-240	35-105		2 to 3	2 to 3	2 to 3		
Tridonic	22176072	230-240	60		1 to 1	1 to 1	1 to 1		
Tridonic	22176074	230-240	105		1 to 3	1 to 3	1 to 3		
Tridonic	Atco 22176070	230-240	60		1 to 1	1 to 1	1 to 1		
Tridonic	Atco Possum 60VA 89400035	230-240	60					1 to 6	1 to 6
Tridonic	Atco Possum 89400085	230-240	60		1 to 1	1 to 1	1 to 1		
Tridonic	Atco Speedy TE-0070 C101	230-240	20-70		1 to 2	1 to 2	1 to 2	1 to 6	1 to 6
Tridonic	Atco TE-0105 C101	230-240	35-105		1 to 3	1 to 3	1 to 3	1 to 6	1 to 6
Tridonic	Atco TE-0105 S003	230-240	105		1 to 3	1 to 3	1 to 3		
Tridonic	Atco Viper 60VA 22176070	230-240	60	1 to 1					
Tridonic	Speedy TE-0105 C101	230-240	35-105	2 to 3					

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
Tridonic	Viper 105 22176074	230-240	105	1 to 3					
Tridonic	Viper 60 22176072	230-240	60	1 to 1					
Tridonic	Viper 60VA 22176110	230	60	1 to 1				1 to 5	1 to 5
TED	WIN-60SLV	220-240	10-60	1 to 1					
TCI	MW 70 LED	230-240	1-70		1 to 2	1 to 2	1 to 2		
TCI	PICO WOLF 60 V.2	230-240	10-60	1 to 1					
TCI	SHARK60	220-240	10-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Tce	Tce 10/23-E	220-240	20-105	3 to 3					
TAO	SET150-2	230	50-150	1 to 4	1 to 4	1 to 4	1 to 4	1 to 6	1 to 6
TAO	TET-E60I	220	60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Tao	TET-E60I	220	20-60	1 to 1					
Sylvania	MINI 60	220-240	20-60	1 to 1					
Sli Sylvania	3006040	240	25-105		1 to 3	1 to 3	1 to 3	1 to 6	1 to 6
Skytronic	VWY-006	170-250	20					1 to 2	1 to 2
Self	SET105F-2	230	35-105	1 to 3	1 to 3	1 to 3	1 to 3		

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
Self	SET70F-2	230	20-70	1 to 2	1 to 2	1 to 2	1 to 2	1 to 6	1 to 6
Self	SET70R	220-240	20-70	1 to 1	1 to 2	1 to 2	1 to 2		
Sector	ALVT60ED	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1		
Robus	LDT150N	230-240	35-150	1 to 4	1 to 4	1 to 4	1 to 4	1 to 6	1 to 6
Robus	LT60d	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1		
Releo	Micro 60 PFS	230-240	10-60		1 to 1	1 to 1	1 to 1		
Reico	RN1613	230-240	100-160	3 to 4				1 to 6	1 to 6
Radium	ET-RALOPOWER	230-240	20-60	1 to 1					
QLT	T105K	230	35-105		1 to 3	1 to 3	1 to 3		
QLT	W60	230	20-60	1 to 1				1 to 6	1 to 6
Puma	ET-075P-230-RD	230-240	35-75					1 to 6	1 to 6
Philips	EHC 075 S	230	20-75		1 to 2	1 to 2	1 to 2		
Philips	EHC250 F	220	35-60	1 to 1					
Philips	ET50 220/12V	170-250	40-60	1 to 1					
Philips	ET-E 10	220-240	2-10(LED)	1 to 1					

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
Philips	ET-S 150 220-240	220-240	50-150		1 to 4	1 to 4	1 to 4	1 to 6	1 to 6
Philips	ET-S 60 220-240	220-240	20-60	1 to 2					
Philips	Primaline 105 230-240	230-240	35-105		1 to 3	1 to 3	1 to 3		
Philips	Primaline 150 230-240	230-240	50-150		1 to 4	1 to 4	1 to 4		
Philips	Primaline 70 230-240	230-240	20-70		1 to 2	1 to 2	1 to 2		
Osram	ET-A 60/220-240	220-240	20-60	1 to 1					
Osram	ET-LED 30	220-240	2-30		1 to 3	1 to 3	1 to 3		
OSRAM	ET-LED 30/220-240	220-240	2-30(LED)	1 to 4					
Osram	ET-P 60/220-240	220-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1		
Osram	ET-PARROT 105/240 I	240	35-105	3 to 3					
Osram	ET-PARROT 70/220-240 I	220-240	20-70	1 to 2	1 to 2	1 to 2	1 to 2		
Osram	ET-Z 60/220-240	220	20-60		1 to 1	1 to 1	1 to 1		
Osram	Halotronic HTM 150/230-240	230-240	35-105		1 to 3	1 to 3	1 to 3		
Osram	Halotronic HTM 70/230-240	230-240	20-70		1 to 2	1 to 2	1 to 2		
Osram	Halotronic HTN 75/230-240	230-240	20-75					1 to 6	1 to 6

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
Osram	IZ-A 50/240	240	50	1 to 1	1 to 1	1 to 1	1 to 1		
Osram	IZ-HALO 50/220-240	220-240	20-50	1 to 1	1 to 1	1 to 1	1 to 1		
Orbit Lighting	ET105G(OL105W)	240	35-105					1 to 6	1 to 6
Orbit Lighting	LET60B	240	10-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Online	Pico Wolf 60	230-240	10-60		1 to 1	1 to 1	1 to 1		
Online	Pico Wolf 70	230-240	70	1 to 1	1 to 2	1 to 2	1 to 2		
Online	Pico Wolf 70	230-240	20-70	1 to 1					
Nvc	ET60DS	220	35-60	1 to 1					
NVC	ET60E	220	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Nobile	EN-110D2	230	35-110	1 to 3	1 to 3	1 to 3	1 to 3	1 to 6	1 to 6
Niko	320-00002	230	50	1 to 1					
Niko	320-00106	230	20-70	1 to 2	1 to 2	1 to 2	1 to 2	1 to 6	1 to 6
Niko	320-00121	230	20-70	2 to 2	1 to 2	1 to 2	1 to 2		
Nelson	Micro 60	230-240	60	1 to 1				1 to 6	1 to 6
Meek	ET-60W	230	60	1 to 1				1 to 6	1 to 6

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
MASSGROVE	MT60	240	20-60	1 to 1					
Lynx	ET-060-LT-230-RD	230-240	35-60					1 to 6	1 to 6
Lucci	TB60L 240 10-60W	240	10-60					1 to 6	1 to 6
Lival	Pico Wolf 60	220-240	60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Lival	Pico Wolf 70	220-240	70	1 to 1	1 to 2	1 to 2	1 to 2		
Lival	Pico Wolf 70	220-240	20-70	1 to 1					
Lite-tech	SY1507/W	220-240	20-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Lite Beetle	LET 105/240LB	240	35-105	1 to 2	1 to 3	1 to 3	1 to 3		
Lightron	ETH-55Eco	240	50	1 to 1	1 to 1	1 to 1	1 to 1		
Lightech	LET 75/12V	230-240	20-75		1 to 2	1 to 2	1 to 2		
Kengo	DET60S	220-240	10-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Kengo	DET-60S	220-240	10-60	1 to 1					
Kengo	Ket105	230-240	35-105	1 to 3	1 to 3	1 to 3	1 to 3		
JCC	JC4030(10-60AV)	220-240	10-60	1 to 1	1 to 1	1 to 1	1 to 1		
Horoz	HL317	220	150		1 to 4	1 to 4	1 to 4		

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
HEP Group	TE105S 20-105W	230-240	20-105	1 to 3					
HEP Group	TE70S 10-70W	230-240	10-70	1 to 2					
HEP Group	TL150S 50-150W	230-240	50-150	1 to 4					
HEP Group	TR70 10-70W	230	10-70	1 to 1					
Halolite	HA-S105	240	35-105		2 to 3	2 to 3	2 to 3		
Halolite	HA-S60TA	220-240	20-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Halolite	HA-SE60	240	20-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Group	TB60I 230 10-60W	230	10-60		1 to 2	1 to 2	1 to 2		
Group	TE105S 20-105W	230-240	20-105	1 to 3	1 to 3	1 to 3	1 to 3		
Group	TE70S 10-70W	230-240	10-70	1 to 2	1 to 2	1 to 2	1 to 2		
Group	TL150S 50-150W	230-240	50-150	1 to 4	1 to 3	1 to 3	1 to 3		
Gira	Tronic-Trafo 0366 00	230	20-70		1 to 2	1 to 2	1 to 2	1 to 6	1 to 6
Gira	Tronic-Trafo 0371 00	230-240	20-105		1 to 3	1 to 3	1 to 3		
Gira	Tronic-Trafo 0378 00	230-240	20-105		1 to 3	1 to 3	1 to 3	1 to 6	1 to 6
Gentech	Pod E60	220-240	20-60					1 to 6	1 to 6






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
GENI	GT-006	170-240	60	1 to 1					
GENERIC	TE12/70 CODE SB1240-B	220-240	70	1 to 2					
Flash Light	HA-105	220-240	35-105		1 to 3	1 to 3	1 to 3	1 to 6	1 to 6
Flash Light	HA-60	220-240	20-60					1 to 6	1 to 6
ERC	TRAEK02	230	20-60	1 to 1	1 to 1	1 to 1	1 to 1		
Enlite	EN-SC60	240	20-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
EMC Sp. z o.o	YT70	230	0-70		1 to 2	1 to 2	1 to 2		
EMC	ET105	230	35-105	1 to 3	1 to 3	1 to 3	1 to 3		
ELT	TCE 5/23-E	230-240	50		1 to 1	1 to 1	1 to 1		
Elt	TR 5/23-01-SC	230	50	1 to 1					
Dura	DELT12060P	230	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Dura	DELT12105M	220-240	35-105	1 to 3					
Dura	DELT12105M	220-240	35-150	1 to 3	1 to 4	1 to 4	1 to 4	1 to 6	1 to 6
Dais	DA-J60	240	10-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Crompton	CBC60	240	60	1 to 1				2 to 6	2 to 6






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER4207R9LN-WFL	ER3207.5d-50H24D ER3207.5d-50H36D	ER2508dLN-FL ER2508dLN-WFL	ER2508dDG-WFL	ER1708d-50H24D ER1708d-50H36D	ER1908d-SP
									
Collingwood	SKY I 60	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Click	TR060	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Cata Plus	CP-2551	220-240	22-60	1 to 1					
Baw	TREH60C1 6-60w	220	6-60	1 to 1					
Barrow	TED20600209-100310	220	20-60	1 to 1					
Aurora	AU-E60	240	10-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Atom	Tiger	230-240	20-60		1 to 1	1 to 1	1 to 1		
Andawo	MR-128	220	20-50	1 to 1	1 to 1	1 to 1	1 to 1		
Anchorn	AET-3502R1	220-240	35-150	1 to 4	2 to 4	2 to 4	2 to 4	1 to 6	1 to 6
Allttx	MT60	230	60	1 to 1	1 to 1	1 to 1	1 to 1		
Allttx	MT60	230	20-60	1 to 1					
Actec	MINI60	230-240	20-60		1 to 1	1 to 1	1 to 1	1 to 6	1 to 6
Actec	VENUS60	230-240	20-60					1 to 6	1 to 6






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
Ushio Group	456001	230	0-60			1 to 1	1 to 1	1 to 1
Unotech	UD-105	220-240	35-105			2 to 3	2 to 3	2 to 3
Tridonic	22176072	230-240	60			1 to 1	1 to 1	1 to 1
Tridonic	22176074	230-240	105			1 to 3	1 to 3	1 to 3
Tridonic	Atco 22176070	230-240	60			1 to 1	1 to 1	1 to 1
Tridonic	Atco Possum 89400085	230-240	60			1 to 1	1 to 1	1 to 1
Tridonic	Atco Speedy TE-0070 C101	230-240	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Tridonic	Atco TE-0105 C101	230-240	35-105			1 to 3	1 to 3	1 to 3
Tridonic	Atco TE-0105 S003	230-240	105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
Tridonic	Atco TE-0105 U 1-10V sc	230-240	20-105	1 to 2	1 to 2			
Tridonic	Atco Viper 60VA 22176070	230-240	60	1 to 1	1 to 1			
Tridonic	Speedy TE-0105 C101	230-240	35-105	1 to 2	1 to 2			
Tridonic	Viper 105 22176074	230-240	105	1 to 2	1 to 2			
Tridonic	Viper 60 22176072	230-240	60	1 to 1	1 to 1			
TED	WIN-60SLV	220-240	10-60	1 to 1	1 to 1			
TCI	MW 70 LED	230	2.5-50	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
TCI	MW 70 LED	230-240	1-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Tci	Pico Wolf 105	230-240	20-105	1 to 2	1 to 2			
TCI	PICO WOLF 60 V.2	230-240	10-60	1 to 1	1 to 1			
TCI	SHARK60	220-240	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
TAO	SET150-2	230	50-150	1 to 3	1 to 3	1 to 4	1 to 4	1 to 4
TAO	TET-E60I	220	60			1 to 1	1 to 1	1 to 1
Sylvania	MINI 60	220-240	20-60	1 to 1	1 to 1			
Sli Sylvania	3006040	240	25-105			1 to 3	1 to 3	1 to 3
Self	SET105F-2	230	35-105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
Self	SET105M	230-240	35-105	1 to 2	1 to 2			
Self	SET70F-2	230	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Self	SET70R	220-240	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Sector	ALVT60ED	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Rutec	Floh ECO 60	220-240	20-60	1 to 1	1 to 1			
Robus	LDT150N	230-240	35-150			1 to 4	1 to 4	1 to 4
Robus	LT60d	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
Robus	RM70DN	220-240	20-70	1 to 1	1 to 1			
RIO	RT060CP	220V	60	1 to 1	1 to 1			
Releo	Micro 60 PFS	230-240	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Radium	ET-RALOPOWER	230-240	20-60	1 to 1	1 to 1			
QLT	T105K	230	35-105			1 to 3	1 to 3	1 to 3
Puma	ET-075P-230-RD	230-240	35-75	1 to 1	1 to 1			
Philips	Certaline 60w	230	20-60	1 to 1	1 to 1			
Philips	EHC 075 S	230	20-75			1 to 2	1 to 2	1 to 2
Philips	EHC250 F	220	35-60	1 to 1	1 to 1			
Philips	ET50 220/12V	170-250	40-60	1 to 1	1 to 1			
Philips	ET-E 60 220-240	220-240	20-60	1 to 1	1 to 1			
Philips	ET-S 150 220-240	220-240	50-150			1 to 4	1 to 4	1 to 4
Philips	Primaline 105 230-240	230-240	35-105			1 to 3	1 to 3	1 to 3
Philips	Primaline 150 230-240	230-240	50-150			1 to 4	1 to 4	1 to 4
Philips	Primaline 70 230-240	230-240	20-70			1 to 2	1 to 2	1 to 2
Paulmann	Mipro 70	230	20-70	1 to 1	1 to 1			






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
Osram	ET-A 60/220-240	220-240	20-60	1 to 1	1 to 1			
Osram	ET-P 60/220-240	220-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	ET-PARROT 105/240 I	240	35-105	1 to 1	1 to 1			
Osram	ET-PARROT 70/220-240 I	220-240	20-70			1 to 2	1 to 2	1 to 2
Osram	ET-Z 60/220-240	220	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	Halotronic HTM 105/230-240	230-240	35-105	1 to 2	1 to 2			
Osram	Halotronic HTM 150/230-240	230-240	35-105	2 to 3	2 to 3	1 to 3	1 to 3	1 to 3
Osram	HALOTRONIC HTM 150/230-240	230-240	50-150	2 to 3	2 to 3	1 to 3	1 to 3	1 to 3
Osram	Halotronic HTM 70/230-240	230-240	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Osram	Halotronic HTN 75/230-240	230-240	20-75	1 to 1	1 to 1			
Osram	IZ-A 50/240	240	50	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Osram	IZ-HALO 50/220-240	220-240	20-50	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Orbit Lighting	LET60B	240	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Orbit	LET60B	240	10-60			1 to 1	1 to 1	1 to 1
Online	Pico Wolf 60	230-240	10-60			1 to 1	1 to 1	1 to 1
Online	Pico Wolf 70	230-240	70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
Online	Pioc Wolf 70	230-240	70			1 to 2	1 to 2	1 to 2
Nvc	ET60DS	220	35-60	1 to 1	1 to 1			
NVC	ET60E	220	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Nobile	EN-110D2	230	35-110	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
Nobile	EN-60D2	230	20-60	1 to 1	1 to 1			
Nobile	EN-80D2	230	20-80	1 to 1	1 to 1			
Niko	320-00106	230	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Niko	320-00121	230	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Nelson	Micro 60	230-240	60	1 to 1	1 to 1			
MP LAMP	T60	220-240	10-60	1 to 1	1 to 1			
Meek	ET-60W	230	60	1 to 1	1 to 1			
Lucci	TB60L 240 10-60W	240	10-60	1 to 1	1 to 1			
Lival	Pico Wolf 60	220-240	60			1 to 1	1 to 1	1 to 1
Lival	Pico Wolf 70	220-240	70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Lival	Pico Wolf 70	220-240	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Lite-tech	SY1507/W	220-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1






Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
Lite Beetle	LET 105/240LB	240	35-105			1 to 3	1 to 3	1 to 3
Lightron	ETH-55Eco	240	50	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Lightech	LET 105/240	240	35-105	1 to 2	1 to 2			
Lightech	LET 75/12V	230-240	20-75	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Kengo	DET-60S	220-240	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Kengo	Ket105	230-240	35-105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
JCC	JC4030(10-60AV)	220-240	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Horoz	HL317	220	150			1 to 4	1 to 4	1 to 4
HEP Group	TB60I 230 10-60W	230	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
HEP Group	TE105S 20-105W	230-240	20-105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
HEP Group	TE70S 10-70W	230-240	10-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
HEP Group	TL150S 50-150W	230-240	50-150	1 to 3	1 to 3	1 to 4	1 to 4	1 to 4
HEP Group	TR70 10-70W	230	10-70	1 to 1	1 to 1			
Halolite	HA-S105	240	35-105			2 to 3	2 to 3	2 to 3
Halolite	HA-S60TA	220-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Halolite	HA-SE60	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
Group	TB60I 230 10-60W	230	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Group	TE105S 20-105W	230-240	20-105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
Group	TE70S 10-70W	230-240	10-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Group	TL150S 50-150W	230-240	50-150	1 to 3	1 to 3	1 to 4	1 to 4	1 to 4
Gira	Tronic-Trafo 0366 00	230	20-70	1 to 1	1 to 1	1 to 2	1 to 2	1 to 2
Gira	Tronic-Trafo 0371 00	230-240	20-105			1 to 3	1 to 3	1 to 3
Gira	Tronic-Trafo 0378 00	230-240	20-105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
Gentech	Pod E60	220-240	20-60	1 to 1	1 to 1			
GENI	GT-006	170-240	60	1 to 1	1 to 1			
GENERIC	TE12/70 CODE SB1240-B	220-240	70	1 to 1	1 to 1			
FLC	ET60A	230	3-60	1 to 1	1 to 1			
Flash Light	HA-105	220-240	35-105			1 to 3	1 to 3	1 to 3
Flash Light	HA-60	220-240	20-60	1 to 1	1 to 1			
ERC	TRAEK02	230	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Enlite	EN-SC60	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Emcolite	EMRED60	240	20-60	1 to 1	1 to 1			

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
EMC Sp. z o.o	YT70	230	0-70			1 to 2	1 to 2	1 to 2
EMC	ET105	230	35-105	1 to 2	1 to 2	1 to 3	1 to 3	1 to 3
ELT	TCE 5/23-E	230-240	50	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Elt	TCE 5/23-E	230-240	20-50	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Elt	TR 5/23-01-SC	230	50	1 to 1	1 to 1			
EICO	E60W	220-240	10-60	1 to 1	1 to 1			
Dura	DELT12060P	230	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Dura	DELT12105M	220-240	35-150	1 to 2	1 to 2	1 to 4	1 to 4	1 to 4
Dais	DA-J60	240	10-60			1 to 1	1 to 1	1 to 1
Dais	DA-J60	240	20-60			1 to 1	1 to 1	1 to 1
Collingwood	SKY I 60	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Click	TR060	240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Baw	TREH60C1 6-60w	220	6-60	1 to 1	1 to 1			
Barrow	TED20600209-100310	220	20-60	1 to 1	1 to 1			
Aurora	AU-E60	240	10-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Atom	Tiger	230-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1

Compatible Halogen Transformer List (tested without Dimmer)

Manufacturer	Model No.	Voltage (V)	Wattage (W)	ER203080/dm-HRv00-SP	ER203080/dm-HRv00-NF ER203080/dm-HRv00-WF	ER3308dLN-SP	ER3308dLN-FL ER3308dR9LN-FL	ER3308dDG-WFL ER3308dR9DG-WFL
								
Andawo	MR-128	220	20-50	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Anchorn	AET-3502R1	220-240	35-150	1 to 3	1 to 3	2 to 4	2 to 4	2 to 4
Allttx	MT60	230	60			1 to 1	1 to 1	1 to 1
Actec	MINI60	230-240	20-60	1 to 1	1 to 1	1 to 1	1 to 1	1 to 1
Actec	VENUS60	230-240	20-60	1 to 1	1 to 1			
ABB	Speedy 70	230-240	20-70	1 to 1	1 to 1			

Remarks:

The minimum and maximum numbers of LED lamp compatible depend upon the performance of the halogen transformer and dimmer, which are subject to the status of the manufacturer's technology. Due to possible variations in country halogen transformer and dimmer modules specifications, please contact your local distributor for a list of compatible halogen transformers and dimmers before installation.
Copyright © MEGAMAN® 2018. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice.
All other trademarks mentioned are the property of their respective owners.